

Scilab Textbook Companion for
Principles Of Electronic Communication
Systems
by L. E. Frenzel¹

Created by
Sagar Ravindra Shinde
B.Tech
Electronics Engineering
Pune University
College Teacher
Prof. Vijay Mane
Cross-Checked by
Ganesh R

July 31, 2019

¹Funded by a grant from the National Mission on Education through ICT, <http://spoken-tutorial.org/NMEICT-Intro>. This Textbook Companion and Scilab codes written in it can be downloaded from the "Textbook Companion Project" section at the website <http://scilab.in>

Book Description

Title: Principles Of Electronic Communication Systems

Author: L. E. Frenzel

Publisher: Tata McGraw - Hill Education, New Delhi

Edition: 3

Year: 2008

ISBN: 0-07-066755-1

Scilab numbering policy used in this document and the relation to the above book.

Exa Example (Solved example)

Eqn Equation (Particular equation of the above book)

AP Appendix to Example(Scilab Code that is an Appednix to a particular Example of the above book)

For example, Exa 3.51 means solved example 3.51 of this book. Sec 2.3 means a scilab code whose theory is explained in Section 2.3 of the book.

Contents

List of Scilab Codes	4
1 Introduction to Electronic communication	5
2 The Fundamentals of Electronics A Review	10
3 Amplitude Modulation Fundamentals	26
4 Amplitude Modulator and Demodulator circuits	31
5 Fundamentals of Frequency Modulation	33
6 FM circuits	37
7 Digital Communication Techniques	40
8 Radio Transmitters	44
9 Communication Receivers	47
10 Multiplexing and Demultiplexing	52
11 The Transmission of Binary data in Communication Systems	54

12 Introduction to Networking and Local Area Network	57
13 Transmission Lines	59
14 Antennas and Wave Propagation	64
16 Microwave Communication	68
17 Satellite Communication	72
19 Optical Communication	74

List of Scilab Codes

Exa 1.1.a	Calculate the wavelength of given frequency	5
Exa 1.1.b	Calculate the Wavelength of given frequency	5
Exa 1.1.c	Calculate the Wavelength of given frequency	6
Exa 1.1.d	Calculate the wavelength of given frequency	6
Exa 1.2	Calculate the frequency of the signal with given wavelength	7
Exa 1.3	Calculate the frequency of the signal	7
Exa 1.4	Calculate the frequency of the electromagnetic wave	8
Exa 1.5	Calculate the bandwidth	8
Exa 1.6	Calculate the upper frequency limit from bandwidth	9
Exa 2.1	Calculate the voltage gain of the amplifier .	10
Exa 2.2	Calculate the input power given to the amplifier	10
Exa 2.3	Calculate the output power of the three cascaded amplifier	11
Exa 2.4	Calculate gain of the second stage of two cascaded amplifiers	11
Exa 2.5.a	Calculate the attenuation	12
Exa 2.5.b	Calculate amplifier gain need to offset the loss for an overall gain of 1	12
Exa 2.6	Calculate the attenuation factor for the amplifier	12
Exa 2.7.a	Calculate the gain of amplifier	13
Exa 2.7.b	Calculate attenuation of the filter	13
Exa 2.8	Calculate the input power given to amplifier	14
Exa 2.9	Calculate the output voltage of the amplifier	14

Exa 2.10	Calculate the power gain for the power amplifier	14
Exa 2.11	Calculate the output power of the amplifier	15
Exa 2.12	Calculate the input voltage given to the circuit consisting of two amplifiers	15
Exa 2.13	Calculate the power in watts	16
Exa 2.14	Calculate the resonant frequency of the circuit	16
Exa 2.15	Calculate the value of inductor required for the resonance of the circuit	17
Exa 2.16	Calculate the bandwidth of the resonant circuit	17
Exa 2.17	Calculate the bandwidth resonant frequency and quality factor of the resonant circuit . .	18
Exa 2.18	Calculate the 3dB down frequencies for the resonant circuit	18
Exa 2.19	Calculate the voltage across the capacitor of the resonant circuit	19
Exa 2.20	Calculate the impedance of the parallel LC circuit	19
Exa 2.21	Calculate the impedance of the circuit . .	20
Exa 2.22	Calculate the value of resistor required to set the bandwidth of a parallel tuned circuit to 1 Mhz	20
Exa 2.23	Calculate the cutoff frequency of the single section RC low pass filter	21
Exa 2.24	Calculate the closest resistor value for the cut-off frequency	21
Exa 2.25	Calculate the value of the capacitor required in RC twin T notch filter	22
Exa 2.26	Calculate the frequency and rms value of the fifth harmonic of the square wave	22
Exa 2.27	Calculate the average dc value signal and the minimum bandwidth necessary to pass signal without excessive distortion	23
Exa 2.28	Calculate the bandwidth required to pass the pulse train	23
Exa 2.29	Calculate the fastest rise time that can passed by the circuit	24

Exa 2.30	Calculate the rise time of the displayed square wave	24
Exa 3.1	Calculate modulation index V_c and V_m for the AM signal	26
Exa 3.2	Calculate the frequencies of the lower and upper sideband of the standard AM broadcast station and also calculate bandwidth	27
Exa 3.3	Calculate the total power and power in one sideband	27
Exa 3.4	Calculate the carrier power total power and sideband power	28
Exa 3.5	Calculate the percentage of modulation	28
Exa 3.6	Calculate the power in one sideband of the transmitter	29
Exa 3.7	Calculate the Peak Envelope Power for the SSB transmitter	29
Exa 3.8	Calculate the Peak Envelope Power and average power of the transmitter	30
Exa 4.1	Calculate the RF input power AF power carrier output power Power in one sideband maximum and minimum dc supply voltage swing	31
Exa 4.2	Calculate the upper and lower sideband ranges of the SSB transmitter and center frequency of a bandpass filter	32
Exa 5.1	Calculate the maximum and minimum frequencies that occur during modulation	33
Exa 5.2	Calculate the deviation of TV sound	33
Exa 5.3	Calculate the maximum modulating frequency	34
Exa 5.4	State the amplitudes of the carrier and four sidebands of FM signal	34
Exa 5.5	Calculate the bandwidth of the FM signal	35
Exa 5.6	Calculate the frequency deviation caused by the noise and improved output signal to noise ratio	36
Exa 6.1	Calculate the value of the inductor required to resonate the circuit	37

Exa 6.2	Calculate the frequency of the carrier crystal oscillator and the phase shift require to produce the necessary deviation	37
Exa 6.3	Calculate two capacitance values require to achieve the total deviation for the FM transmitter	38
Exa 7.1	Calculate the signal frequency fourth harmonic and minimum sampling frequency	40
Exa 7.2	Calculate the number of discrete levels represented by the ADC Number of voltage increments used to divide the voltage range and the resolution of the digitization	41
Exa 7.3	Calculate the SINAD and ENOB	41
Exa 7.4	Calculate the output voltage and gain of the compander	42
Exa 7.5	Calculate the output voltage and gain of the compander	42
Exa 8.1	Calculate the maximum and the minimum frequencies of the crystal given the stability of the crystal	44
Exa 8.2	Calculate output frequency of the transmitter and maximum and minimum frequencies that can be achieved by the transmitter	44
Exa 8.3	Calculate the output frequency of the synthesizer	45
Exa 8.4	Find that step change in the output frequency of the synthesizer is equal to the phase detector reference range	46
Exa 9.1	Calculate the local oscillator tuning range the frequency of the second local oscillator and first IF image frequency range of the Superheterodyne receiver	47
Exa 9.2	Calculate the open circuit noise voltage	48
Exa 9.3	What is the input thermal noise voltage of a receiver	48
Exa 9.4	Calculate the average noise power of a device	49
Exa 9.5	Calculate the noise factor and noise figure of the RF amplifier	49

Exa 9.6	Calculate the input noise power the input signal power signal to noise ratio in decibels for receiver and noise factor signal to noise ratio and noise temperature for the amplifier	50
Exa 10.1	Calculate the number of cahnnels carried by the cable TV service	52
Exa 10.2	Calculate the number of available data channels number of bits per frame serial data rate for the PCM system	52
Exa 11.1	Calculate the time required to transmit single word single bit and speed of transmission for the serially transmitted data	54
Exa 11.2	Calculate the maximum theoretical data rate the maximum theoretical channel capacity and the number coding levels required to achieve the maximum speed	55
Exa 11.3	Calculate the average number of errors that can be expected in the transmission	55
Exa 12.1	Calculate the number of interconnecting wires required to communicate with each PC in the office	57
Exa 12.2	Calculate the time required for the transmission of data on Ethernet packet and Token ring packet	57
Exa 13.1	1 Calculate the length of the cable considered to be a transmission line	59
Exa 13.2	Calculate the physical length of the transmission line	59
Exa 13.3	Calculate the total attenuation and output power of the antenna	60
Exa 13.4	Calculate the load impedance equivalent inductance time delay phase shift and total attenuation of the cable	60
Exa 13.5	Calculate the SWR reflection coefficient and value of resistive load	61
Exa 13.6	Calculate the output power of the cable	62

Exa 13.7	Calculate the characteristics impedance of the microstrip transmission line and the reactance of the capacitor	62
Exa 13.8	Calculate the length of the transmission line	63
Exa 14.1	Calculate the length and radiation resistance for different antennas	64
Exa 14.2	Calculate the transmission line loss and effective radiated power	65
Exa 14.3	Calculate the length of the impedance matching section	65
Exa 14.4	Calculate the length of the impedance matching section	66
Exa 14.5	Calculate the maximum transmitting distance and received power at that distance	66
Exa 16.1	Calculate the required impedance of the microstrip and its length	68
Exa 16.2	Calculate the cutoff frequency and operating frequency of the rectangular waveguide	68
Exa 16.3	Criterion for the operation of rectangular waveguide in the C band	69
Exa 16.4	Calculate the lowest possible operating frequency gain and beam width for the parabolic reflector	69
Exa 16.5	Calculate line of sight distance to aircraft and the altitude of the aircraft	70
Exa 17.1	Calculate the approximate azimuth and elevation setting of the antenna	72
Exa 17.2	Calculate the uplink frequency and the maximum theoretical data rate of satellite transponder	72
Exa 17.3	Calculate local oscillator frequency to achieve the desired IF	73
Exa 19.1	Calculate the critical angle of the fiber optic cable	74
Exa 19.2	Calculate the bandwidth of the cable	74
Exa 19.3	Calculate the dispersion factor of the fiber optic cable	75

Chapter 1

Introduction to Electronic communication

Scilab code Exa 1.1.a Calculate the wavelength of given frequency

```
1 //Example 1-1 a, Page No - 14
2
3 clear
4 clc
5
6 c=3000000000
7 f=1500000000
8
9 wavelength = c/f
10
11 printf('Wavelength is %.3f meter ',wavelength)
```

Scilab code Exa 1.1.b Calculate the Wavelength of given frequency

```
1 //Example 1-1 b, Page No - 14
2
```

```
3 clear
4 clc
5
6 c=3000000000
7 f=4300000000
8
9 wavelength = c/f
10
11 printf('Wavelength is %.3f meter ',wavelength)
```

Scilab code Exa 1.1.c Calculate the Wavelength of given frequency

```
1 //Example 1-1 c, Page No - 14
2
3 clear
4 clc
5
6 c=3000000000
7 f=8000000
8
9 wavelength = c/f
10
11 printf('Wavelength is %.3f meter ',wavelength)
```

Scilab code Exa 1.1.d Calculate the wavelength of given frequency

```
1 //Example 1-1 d, Page No - 14
2
3 clear
4 clc
5
6 c=3000000000
7 f=750000
```

```
8
9 wavelength = c/f
10
11 printf('Wavelength is %.3f meter',wavelength)
```

Scilab code Exa 1.2 Calculate the frequency of the signal with given wavelength

```
1 //Example 1-2, Page No - 15
2
3 clear
4 clc
5
6 c=300000000
7 wavelength=1.5
8
9 frequency=c/wavelength
10
11 printf('Signal frequency is %.3f Megahertz',frequency
        /1000000)
```

Scilab code Exa 1.3 Calculate the frequency of the signal

```
1 //Example 1-3, Page No - 15
2
3 clear
4 clc
5
6 wavelength_feet=75
7 wavelength_meter= 75/3.28
8 c=300000000
9
10 frequency=c/wavelength_meter
11
```

```
12 printf('The signal frequency is %.3f Megahertz ',  
        frequency/1000000)
```

Scilab code Exa 1.4 Calculate the frequency of the electromagnetic wave

```
1 //Example 1-4, Page No - 15  
2  
3 clear  
4 clc  
5  
6 wavelength_inches=8  
7 wavelength_meter= 8/39.37  
8 c=300000000  
9  
10 frequency= c/wavelength_meter  
11  
12 printf('\nThe signal frequency is %.3f Megahertz ',  
        frequency/1000000)  
13 printf('\nThe signal frequency is %.3f Gigahertz ',  
        frequency/1000000000)
```

Scilab code Exa 1.5 Calculate the bandwidth

```
1 //Example 1-5, Page No - 18  
2  
3 clear  
4 clc  
5  
6 f1=902000000  
7 f2=928000000  
8  
9 bandwidth=f2-f1  
10
```

```
11 printf('Width of the band is %d Megahertz ',bandwidth
    /1000000)
```

Scilab code Exa 1.6 Calculate the upper frequency limit from bandwidth

```
1 //Example 1-6, Page No - 19
2
3 clear
4 clc
5
6 bandwidth_megahertz= 6
7 f1_megahertz=54
8 f2_megahertz=f1_megahertz + bandwidth_megahertz
9
10 printf('Upper frequency limit is %.3f Megahertz ',
    f2_megahertz)
```

Chapter 2

The Fundamentals of Electronics A Review

Scilab code Exa 2.1 Calculate the voltage gain of the amplifier

```
1 clc
2 clear
3 vout=750*10^-3
4 vin = 30*10^-6
5 gain=vout/vin
6 printf('The Voltage gain of the amplifier is %.1f',
    gain)
```

Scilab code Exa 2.2 Calculate the input power given to the amplifier

```
1 //
2 clear
3 clc
4
5 pout=6
6 power_gain=80
```

```
7
8 pin=pout/power_gain
9
10 printf('The input power of the signal is %.1f mW',
        pin*1000)
```

Scilab code Exa 2.3 Calculate the output power of the three cascaded amplifier

```
1 clc;
2 clear;
3 A1=5;
4 A2=2;
5 A3=17;
6 total_gain=A1*A2*A3;
7 pin= 40*10^-3;
8 pout=total_gain*pin;
9 printf('The output power is %.1f watts',pout);
```

Scilab code Exa 2.4 Calculate gain of the second stage of two cascaded amplifiers

```
1 clc;
2 clear;
3 pin=25*10^-6;
4 pout=1.5*10^-3;
5 A1=3;
6 total_gain=pout/pin;
7 printf('\nTotal gain is %.1f',total_gain);
8 A2=total_gain/A1;
9 printf('\nThe gain of second stage is %.1f',A2);
```

Scilab code Exa 2.5.a Calculate the attenuation

```
1 clc;
2 clear;
3 R1=10*10^3;
4 R2=470;
5 attenuation=R2/(R2+R1);
6 printf('The attenuation is %.3f',attenuation);
```

Scilab code Exa 2.5.b Calculate amplifier gain need to offset the loss for an over

```
1 clc;
2 clear;
3 A1=0.045;
4 AT=1;
5 A2=AT/A1;
6 printf('\n\nThe amplifier gain need to offset the loss
        for overall gain of 1 is %.1f',A2);
```

Scilab code Exa 2.6 Calculate the attenuation factor for the amplifier

```
1 clc;
2 clear;
3 Vin=20*10^-6;
4 Vout=100*10^-3;
5 A1=45000; //A1 is Amplifier gain
6 AT=Vout/Vin; //AT is Total gain
7 printf('\n\nTotal gain is %.3f',AT);
8 A2=AT/A1; //A2 is attenuation factor
9 printf('\n\nThe atenuation factor needed to to keep
        the output \nvoltage from exceeding 100 mv is %.4
        f',A2);
```

Scilab code Exa 2.7.a Calculate the gain of amplifier

```
1 //Example 2-7 a, Page No.36
2
3 clear
4 clc
5
6 Vin=3*10^-3
7 Vout=5
8
9 gain_dB= 20*log10 (Vout/Vin)
10
11 printf('The gain of amplifier in dB is %.1f',gain_dB
    )
```

Scilab code Exa 2.7.b Calculate attenuation of the filter

```
1 //Example 2-7 b, Page No.36
2
3 clear
4 clc
5
6 pin_mW = 50
7 pout_mW = 2
8
9 gain_dB= 10*log10(pout_mW/pin_mW)
10
11 printf('The gain/attenuation of the amplifier is %.2
    f',gain_dB)
```

Scilab code Exa 2.8 Calculate the input power given to amplifier

```
1 //Example 2-8, Page No- 38
2
3 clear
4 clc
5
6 gain_dB = 40
7 pout_W= 100
8
9 pin_W = pout_W/10^4
10
11 printf('The input power is %.2f watt',pin_W);
```

Scilab code Exa 2.9 Calculate the output voltage of the amplifier

```
1 //Example 2-9, Page No- 38
2
3 clear
4 clc
5
6 gain_db = 60
7 vin = 50*10^-6
8
9 vout = 10^(60/20)*vin
10
11 printf('The output voltage is %.2f volt',vout);
```

Scilab code Exa 2.10 Calculate the power gain for the power amplifier

```
1 //Example 2-10. Page No - 39
2
3 clear
```

```

4  clc
5
6  vin=90*10^-3
7  R1= 10*10^3
8  vout=7.8
9  Rout=8
10
11 pin= vin^2/R1
12 pout=vout^2/Rout
13
14 Ap_db = 10*log10 (pout/pin)
15
16 printf('The power gain in decibel is %.1f dB',Ap_db)

```

Scilab code Exa 2.11 Calculate the output power of the amplifier

```

1  //Example 2-11, Page No - 40
2
3  clear
4  clc
5
6  gain_db = 28
7  pin = 36*10^-3
8
9  pout = 10^2.8*pin;
10
11 printf('The output power is %.2f watt',pout)

```

Scilab code Exa 2.12 Calculate the input voltage given to the circuit consisting o

```

1  //Example 2-12, Page No - 40
2
3  clear

```

```
4 clc
5
6 gain1 = 6.8
7 gain2 = 14.3
8 attenuation1 = -16.4
9 attenuation2 = -2.9
10 vout = 800*10^-3
11
12 At = gain1+gain2+attenuation1+attenuation2
13 vin = vout/10^(At/20)
14
15 printf('The input voltage is %.1f mV',vin*10^3)
```

Scilab code Exa 2.13 Calculate the power in watts

```
1 //Example 2-13, Page No - 40
2
3 clear
4 clc
5
6 pout_db =12.3
7
8 pout_mW = 0.001*10^(12.3/10)
9
10 printf('The output power is %.1f mW',pout_mW*10^3)
```

Scilab code Exa 2.14 Calculate the resonant frequency of the circuit

```
1 //Example 2-14, Page No - 46
2
3 clear
4 clc
5
```

```

6 c = 2.7*10^-12
7 l = 33*10^-9
8
9 fr= 1/(6.28*(l*c)^0.5)
10
11 printf('The resonat frequency is %.1f Mhz',fr/10^6)

```

Scilab code Exa 2.15 Calculate the value of inductor required for the resonance of

```

1 //Example 2-15, Page No - 47
2
3 clear
4 clc
5
6 c =12*10^-12
7 fr = 49*10^6
8
9 l=1/(4*3.14^2*fr^2*c)
10
11 printf('The value of inductance is %.1f nH',l*10^9)

```

Scilab code Exa 2.16 Calculate the bandwidth of the resonant circuit

```

1 //Example 2-16, page No-49
2
3 clear
4 clc
5
6 fr=28*10^6
7 Q=70
8
9 bandwidth = fr/Q
10

```



```
11 printf('The bandwidth is %.3f Khz ',bandwidth/10^3)
```

Scilab code Exa 2.17 Calculate the bandwidth resonant frequency and quality factor

```
1 //Example 2-17, Page No - 50
2
3 clear
4 clc
5
6 f1= 7.93*10^6
7 f2= 8.07*10^6
8
9 bw= f2-f1
10 fr=(f1*f2)^0.5
11 Q= fr/bw
12
13 printf('\\n The bandwidth is %.1f Khz ',bw/10^3)
14 printf('\\n The resonant frequency is %.1f Mhz',fr
    /10^6)
15 printf('\\n The Q of resonant circuit is %.2f',Q)
```

Scilab code Exa 2.18 Calculate the 3dB down frequencies for the resonant circuit

```
1 //Example 2-18, Page No - 50
2
3 clear
4 clc
5
6 Q=200
7 fr=16*10^6
8
9 bw=fr/Q
10 f1= fr-(bw/2)
```

```

11 f2=fr+(bw/2)
12
13 printf('The 3 db down frequencies of the resonant
    circuit are \nf1=%0.2f Mhz\t f2=%0.2f Mhz',f1/10^6,
    f2/10^6)

```

Scilab code Exa 2.19 Calculate the voltage across the capacitor of the resonant ci

```

1 //Example 2-19, Page No - 52
2
3 clear
4 clc
5
6 Q= 150
7 Vs=3*10^-6
8
9 Vc= Q*Vs
10
11 printf('The voltage across capacitor is %0.1f
    microvolt ',Vc*10^6)

```

Scilab code Exa 2.20 Calculate the impedance of the parallel LC circuit

```

1 //Example 2-20, Page No - 54
2
3 clear
4 clc
5
6 fr= 52*10^6
7 Q=12
8 L=0.15*10^-6
9
10 Rw=(6.28*fr*L)/Q

```

```

11 Req= Rw*(Q^2+1)
12
13 printf('Impedance of the parellel LC circuit is %.1f
        ohm',Req)

```

Scilab code Exa 2.21 Calculate the impedance of the circuit

```

1 //Example 2-21, Page no - 54
2 clear
3 clc
4
5 fr= 52*10^6
6 Rw= 4.1
7 L =0.15*10^-6
8
9 Z = L/((1/(4*3.14^2*fr^2*L))*Rw)
10
11 printf('the impedance of the circuit is %.1f ohm',Z)

```

Scilab code Exa 2.22 Calculate the value of resistor required to set the bandwidth

```

1 //Example 2-22, page no - 55
2
3 clear
4 clc
5
6 bw = 1*10^6
7 XL = 300
8 Rw = 10
9 fr =10*10^6
10
11 Q1 = XL/Rw
12 Rp = Rw*(Q1^2+1)

```

```

13
14 Q2 = fr/bw
15 Rpnew = Q2*XL
16
17 Rext = (Rpnew*Rp)/(Rp-Rpnew)
18
19 printf('The value of resistor needed to set the
    bandwidth of \nthe parellel tuned circuit to 1
    Mhz is %.1f ohm',Rext)

```

Scilab code Exa 2.23 Calculate the cutoff frequency of the single section RC low p

```

1 //Example 2-23, Page No - 55
2
3 clear
4 clc
5
6 R = 8.2*10^3
7 C =0.0033*10^-6
8
9 fco = 1/(6.28* R*C)
10
11 printf('The cut off frequency is %.2f Khz',fco/10^3)

```

Scilab code Exa 2.24 Calculate the closest resistor value for the cutoff frequency

```

1 //Example 2-24, Page No - 57
2
3 clear
4 clc
5
6 fco =3.4*10^3
7 C = 0.047*10^-6

```

```

8 R = 1/(6.28* fco* C)
9
10 printf('The value of the resistor is %.1f ohm', R)
11 printf('\n\nThe closest standard value is 1000 ohm ')

```

Scilab code Exa 2.25 Calculate the value of the capacitor required in RC twin T no

```

1 //Example 2-25, page no - 61
2
3 clear
4 clc
5
6 fnotch = 120
7 R = 220*10^3
8
9 C = 1/(6.28*R*fnotch)
10
11 printf('The value of capacitance required is %.3f
    microfarad ',2*C*10^6)

```

Scilab code Exa 2.26 Calculate the frequency and rms value of the fifth harmonic o

```

1 //Example 2-26,Page No - 82
2
3 clear
4 clc
5
6 Vpeak =3
7 f=48*10^3
8
9 fifth_harmonic = 5*f
10 Vrms=(4/3.14)*(3/5)*0.707
11

```

```

12 printf('The frequency of the fifth harmonic is %.1f
    Khz',fifth_harmonic/10^3)
13 printf('\n The RMS voltage of the fifth harmonic is
    %.2f',Vrms)

```

Scilab code Exa 2.27 Calculate the average dc value signal and the minimum bandwidth

```

1 //Example 2-27, page No - 87
2
3 clear
4 clc
5
6 Vpeak = 5
7 f = 4*10^6
8 duty_cycle=0.3
9
10 T = 1/f
11 t0 = duty_cycle*T
12 Vavg = Vpeak*duty_cycle
13 min_bw =1/t0
14
15 printf('The average DC value is %.1f volt ',Vavg)
16 printf('\n The minimum bandwidth required is %.3f
    Mhz',min_bw/10^6)

```

Scilab code Exa 2.28 Calculate the bandwidth required to pass the pulse train

```

1 //Example 2-28, Page No - 88
2
3 clear
4 clc
5
6 tr =6*10^-9

```

```

7
8 min_bw=(35/0.006)
9
10 printf('The minimum bandwidth is %.1f Mhz',min_bw
        /10^2)

```

Scilab code Exa 2.29 Calculate the fastest rise time that can passed by the circuit

```

1 //Example 2-29, Page No - 89
2
3 clear
4 clc
5
6 bw= 200*10^3
7
8 tr= 0.35/(bw*10^-3)
9
10 printf('The fastest rise time of the circuit is %.2f
        microseconds',tr*10^3)

```

Scilab code Exa 2.30 Calculate the rise time of the displayed square wave

```

1 //Example 2-30, Page no - 90
2
3 clear
4 clc
5
6 bw_mhz = 60
7 tri_ns= 15
8
9 tra_osci = 0.35/(bw_mhz)
10 tra_comp = 1.1*(tri_ns^2 + (tra_osci*10^3)^2)^0.5
11

```

```
12 printf('The rise time of the displayed square wave  
    is %.1f ns',tra_comp)
```

Chapter 3

Amplitude Modulation Fundamentals

Scilab code Exa 3.1 Calculate modulation index V_c and V_m for the AM signal

```
1 //Example 3-1, Page No - 99
2
3 clear
4 clc
5
6 Vmax = 5.9
7 Vmin = 1.2
8
9 m = (Vmax-Vmin)/(Vmax+Vmin)
10 Vc = (Vmax+Vmin)/2
11 Vm = (Vmax-Vmin)/2
12
13 m = Vm/Vc
14 printf('The modulation index is %.3f',m)
15 printf('\n Vc=%.1f\tVm=%.1f (for 2 volt/div on
    verticle scale) ',Vc,Vm)
```

Scilab code Exa 3.2 Calculate the frequencies of the lower and upper sideband of t

```
1 //Example 3-2 ,Page No - 102
2
3 clear
4 clc
5
6 frq =980*10^3
7 frq_range = 5*10^3
8
9 fusb = frq+frq_range
10 flsb = frq-frq_range
11 bw=fusb-flsb
12
13 printf('The upper sideband is at %.1f Khz\n Lower
        sideband is at %.1f Khz\n and the babdwidth is %
        .1f Khz ',fusb/10^3,flsb/10^3,bw/10^3)
```

Scilab code Exa 3.3 Calculate the total power and power in one sideband

```
1 //Example 3-3, Page No - 106
2
3 clear
4 clc
5
6 Pc = 30
7 m=0.85
8
9 Pt = Pc*(1+ (m^2/2))
10
11 Psb_both =Pt-Pc
12 Psb_one = Psb_both/2
13
14 printf('The total power is %.1f watt \n The power in
        one sideband is %.1f watt ',Pt,Psb_one)
```

Scilab code Exa 3.4 Calculate the carrier power total power and sideband power

```
1 //Example 3-4, Page No - 108
2
3 clear
4 clc
5
6 R = 40
7 I = 4.8
8 m=0.9
9
10 Pc = I^2*R
11 Pt = (I*(1+(m^2/2)))^0.5)^2*R
12 Psb = Pt-Pc
13
14 printf('The carrier power is %.1f watt\n Total power
        = %.1f watt\n Sideband Power =%.1f watt ',Pc,Pt,
        Psb)
```

Scilab code Exa 3.5 Calculate the percentage of modulation

```
1 //Example 3-5, Page No - 108
2
3 clear
4 clc
5
6 It = 5.1
7 Ic =4.8
8
9 m=(2*((It/Ic)^2-1))^0.5
10
11 printf('The percentage of modulation is %.1f ',m*100)
```

Scilab code Exa 3.6 Calculate the power in one sideband of the transmitter

```
1 // Example 3-6, Page No - 109
2
3 clear
4 clc
5
6 m = 0.9
7 Pc = 921.6
8
9 Psb = (m^2*Pc)/4
10
11 printf('The power in one sideband %.1f watt ',Psb)
```

Scilab code Exa 3.7 Calculate the Peak Envelop Power for the SSB transmitter

```
1 //Example 3-7,Page No- 113
2
3 clear
4 clc
5
6 Vpp = 178
7 R = 75
8
9 Vp =Vpp/2
10 Vrms = 0.707*Vp
11 PEP =(Vrms^2/R)
12
13 printf('The peak envelop power is %0.1f watt ', PEP)
```

Scilab code Exa 3.8 Calculate the Peak Envelope Power and average power of the tra

```
1 //Example 3-8,Page No - 113
2
3 clear
4 clc
5
6 Vs =24
7 Im =9.3
8
9 PEP = Vs*Im
10 Pavg1 = PEP/3
11 Pavg2 = PEP/4
12
13 printf('The peak envelope power is %.1f watt\n
        Average power of transmitter is %.1f watt to %.1f
        watt ',PEP,Pavg2,Pavg1)
```

Chapter 4

Amplitude Modulator and Demodulator circuits

Scilab code Exa 4.1 Calculate the RF input power AF power carrier output power Power

```
1 //Example 4-1, Page No - 129
2
3 clear
4 clc
5
6 Vcc =48
7 I = 3.5
8 effi_percent=70
9 modulation_percent= 67
10 m = modulation_percent/100
11
12 Pi = Vcc*I
13 Pc=Pi
14 Pm = Pi/2
15 Pout = (effi_percent*Pi)/100
16 Ps = Pc*((m^2)/4)
17 max_swing = 2*Vcc
18
19 printf('The input power is %.1f watt \n AF power
```

```

    required for the 100 percent modulation is %.1f
    watt \n The carrier output power is %.1f watt\n',
    Pi,Pm,Pout)
20 printf('The power in one sideband %.2f watt \n
    Maximum swing = %.1f volt\n Minimum swing =0.0
    volt ',Ps,max_swing)

```

Scilab code Exa 4.2 Calculate the upper and lower sideband ranges of the SSB trans

```

1 //Example 4-2,Page NO - 145
2
3 clear
4 clc
5
6 fc =4.2*10^6
7 voice_f_l = 300
8 voice_f_u = 3400
9
10 fll_usb = fc + voice_f_l
11 ful_usb = fc + voice_f_u
12
13 fll_lsb = fc - voice_f_l
14 ful_lsb = fc - voice_f_u
15
16 flsb = (fll_lsb + ful_lsb)/2
17
18 printf('The range for USB is %.1f Hz to %.1f Hz',
    fll_usb,ful_usb)
19 printf('\n The range for LSB is %.1f Hz to %.1f Hz',
    fll_lsb,ful_lsb)
20 printf('\n The approximate center frequency of the
    filter \n to select the lower sideband is %.1f Hz
    ',flsb)

```

Chapter 5

Fundamentals of Frequency Modulation

Scilab code Exa 5.1 Calculate the maximum and minimum frequencies that occur during

```
1 //Example 5-1 Page No - 153
2
3 clear
4 clc
5
6 f = 915*10^6
7 fm_deviation =12.5*10^3
8
9 max_deviation = f + fm_deviation
10 min_deviation = f - fm_deviation
11
12 printf('Maximum frequency occur during modulation is
        %.1f Khz ',max_deviation/1000)
13 printf('\n Minimum frequency occur during modulation
        is %.1f Khz ',min_deviation/1000)
```

Scilab code Exa 5.2 Calculate the deviation of TV sound

```
1 //Example 5-2, Page No - 160
2
3 clear
4 clc
5
6 max_deviation = 25*10^3
7 fm =15*10^3
8
9 mf =max_deviation/fm
10
11 printf('The deviation ratio of the TV sound is %.3f'
        ,mf)
```

Scilab code Exa 5.3 Calculate the maximum modulating frequency

```
1 //Example 5-3, Page No - 162
2
3 clear
4 clc
5
6 mf = 2.2
7 fd = 7.48*10^3
8
9 fm = fd/mf
10
11 printf('The maximum modulating frequency is %.1f Khz
        ',fm/1000)
```

Scilab code Exa 5.4 State the amplitudes of the carrier and four sidebands of FM si

```
1 //Example 5-4, Page No - 164
```

```

2
3 clear
4 clc
5
6 J0 = -0.4
7 J1 = -0.07
8 J2 = 0.36
9 J3 = 0.43
10 J4 = 0.28
11
12 printf('The amplitude of the carrier is %.1f',J0)
13 printf('\n Amplitudes of the first four sidebands
    are \n%.2f\t %.2f\t %.2f\t %.2f',J1,J2,J3,J4)

```

Scilab code Exa 5.5 Calculate the bandwidth of the FM signal

```

1 //Example 5-5, page No - 165
2
3 clear
4 clc
5
6 fd = 30*10^3
7 fm = 5*10^3
8 N=9
9
10
11 bw1 = 2*fm*N
12 bw2 = 2*[fd+fm]
13
14 printf('The maximum bandwidth of the fm signal
    calculated from fig 5.8 is %.1f Khz',bw1/10^3)
15 printf('\n The maximum bandwidth using carlos rule
    is %.1f khz',bw2/10^3)

```

Scilab code Exa 5.6 Calculate the frequency deviation caused by the noise and impr

```
1 //Example 5-6, Page No - 167
2
3 clear
4 clc
5
6 S_N = 2.8
7 fm = 1.5*10^3
8 fd =4*10^3
9
10 fi= asin(1/S_N)
11 delta = fi*fm
12 SN =fd/delta
13
14 printf('The frequency deviation caused by the noise
        %.3f Hz',delta)
15 printf('\n The improved output signal to noise ratio
        is %.1f ',SN)
```

Chapter 6

FM circuits

Scilab code Exa 6.1 Calculate the value of the inductor required to resonate the c

```
1 //Example 6-1, Page No - 178
2
3 clear
4 clc
5
6 Vc =40*10^-12
7 c = 20*10^-12
8 f0 = 5.5*10^6
9 Ct = Vc+c
10
11 L = 1/((6.28*f0)^2*Ct)
12
13 printf('The value of the inductance is %.2f
        microhenry ',L*10^6)
```

Scilab code Exa 6.2 Calculate the frequency of the carrier crystal oscillator and

```
1 //Example 6-2, Page No - 186
```

```

2
3 clear
4 clc
5
6 f=168.96*10^6
7 multiplier=24
8 deviation = 5*10^3
9 fm = 2.8*10^3
10 f0 =f/multiplier
11 fd= deviation/multiplier
12
13 phaseshift = fd/fm
14 phaseshift_degrees = phaseshift*57.3
15 total_phaseshift =2*phaseshift_degrees
16
17 printf('The crystal oscillator frequency is %.2f Mhz
        ',f0/10^6)
18 printf('\n The total phase shift is %.3f degrees',
        total_phaseshift)

```

Scilab code Exa 6.3 Calculate two capacitance values require to achieve the total

```

1 //Example 6-3, Page No - 187
2
3 clear
4 clc
5
6 R =1*10^3
7 phaseshift =4.263
8 phaseshift_center= 45
9 f =7.04*10^6
10
11 phase_l = phaseshift_center - phaseshift
12 phase_u = phaseshift_center + phaseshift
13 phaserange_total = phase_u - phase_l

```

```
14
15 Xc1 = 1161
16 C1 = 1/(6.28*f*Xc1)
17 Xc2 = 861
18 C2 = 1/(6.28*f*Xc2)
19
20 printf('The two values of the capacitance to achieve
    total \nde viation are %.2f to %.2f picofarad ',C1
    *10^12,C2*10^12)
```

Chapter 7

Digital Communication Techniques

Scilab code Exa 7.1 Calculate the signal frequency fourth harmonic and minimum sam

```
1 //Example 7-1, Page No - 210
2
3 clear
4 clc
5
6 t = 71.4*10^-6
7
8 f = 1/t
9 fourth_harmonic = f*4
10 min_sampling = 2*fourth_harmonic
11
12 printf('The frequency of the signal is %.1f Khz',f
        /10^3)
13 printf('\n The fourth harmonic is %.1f Khz ',
        fourth_harmonic/10^3)
14 printf('\n Minimum sampling rate is %.1f khz',
        min_sampling/10^3)
```

Scilab code Exa 7.2 Calculate the number of discrete levels represented by the ADC

```
1 //Example 7-2, Page no - 222
2
3 clear
4 clc
5
6 N = 14
7 discrete_levels = 2^N
8 num_vltg_inc = 2^N-1
9 resolution = 12/discrete_levels
10
11 printf('The number of discrete levels that are
        represented \n using N number of bits are %d',
        discrete_levels)
12 printf('\n the number of voltage increments
        required to divide \n the voltage range are %d',
        num_vltg_inc)
13 printf('\n Resolution of the digitization %.1f
        microvolt ',resolution*10^6)
```

Scilab code Exa 7.3 Calculate the SINAD and ENOB

```
1 //Example 7-3, Page No - 225
2
3 clear
4 clc
5
6 N =12
7 SINAD1=78
8 SINAD2 = 6.02*N + 1.76
9 ENOB =(SINAD1 -1.76)/6.02
```



```

10
11 printf('The SINAD for 12 bit convertre is %d dB',
        SINAD2)
12 printf('\n The ENOB for the converter with SINAD of
        78 dB is %.2f bits ',ENOB)

```

Scilab code Exa 7.4 Calculate the output voltage and gain of the compander

```

1 //Example 7-4,Page No - 233
2
3 clear
4 clc
5
6 Vm = 1
7 Vin = 0.25
8 mu =255
9
10 Vout = (Vm*log(1+mu*(Vin/Vm)))/log(1+mu)
11 gain =Vout/Vin
12
13 printf('The output voltage of the compander %.2f
        volt ',Vout)
14 printf('\n Gain of the compander is %d',gain)

```

Scilab code Exa 7.5 Calculate the output voltage and gain of the compander

```

1 //Example 7-5, Page No - 234
2
3 clear
4 clc
5
6 Vin = 0.8
7 Vm =1

```

```
8 mu =255
9
10 Vout = (Vm*log(1+mu*(Vin/Vm)))/log(1+mu)
11 gain =Vout/Vin
12
13 printf('The output voltage of the compander %.2f
        volt ',Vout)
14 printf('\n Gain of the compander is %.1f',gain)
```

Chapter 8

Radio Transmitters

Scilab code Exa 8.1 Calculate the maximum and the minimum frequencies of the crystal

```
1 //Example 8-1, Page No - 249
2
3 clear
4 clc
5
6 f = 16*10^6
7 ppm = 200
8
9 frequency_variation = 200 *16
10
11 min_f = f - frequency_variation
12 max_f = f + frequency_variation
13
14 printf('The minimum and maximum frequencies for the
        crystal of \n 16 Mhz with stability of 200 are %d
        Hz and %d Hz respectively ',min_f,max_f)
```

Scilab code Exa 8.2 Calculate output frequency of the transmitter and maximum and

```

1 //Example 8-2, Page No - 250
2
3 clear
4 clc
5
6 f =14.9*10^6
7 mul_factor = 2*3*3
8 stability_ppm =300
9 variation = 0.0003
10 total_variation = variation* mul_factor
11
12 fout = f * mul_factor
13 frequency_variation = fout*total_variation
14
15 f_lower = fout - frequency_variation
16 f_upper = fout + frequency_variation
17
18 printf('The output frequency of the transmitter is %
    .1 f Mhz',fout/10^6)
19 printf('\n The maximum and minimum frequencies of
    the transmitter are \n %.2f Mhz and %.2f Mhz ',
    f_lower/10^6,f_upper/10^6)

```

Scilab code Exa 8.3 Calculate the output frequency of the synthesizer

```

1 //Example 8-3, Page No - 259
2
3 clear
4 clc
5
6 f = 10*10^6
7 div_factor = 100
8 A =63
9 N = 285
10 M=32

```

```

11
12 ref = f/div_factor
13 R =M*N+A
14 fout= R*ref
15
16 printf('The output frequency of the synthesizer is %
    .1f Mhz',fout/10^6)

```

Scilab code Exa 8.4 Find that step change in the output frequency of the synthesizer

```

1 //Example 8-4, Page No - 259
2
3 clear
4 clc
5
6 f = 10*10^6
7 div_factor = 100
8 A =64
9 N = 285
10 M=32
11
12 ref = f/div_factor
13 R =M*N+A
14 fout= R*ref
15
16 printf('The output frequency of the synthesizer is %
    .1f Mhz',fout/10^6)
17 printf('\n The step change is %.1f Mhz ',fout
    /10^6-918.3)

```

Chapter 9

Communication Receivers

Scilab code Exa 9.1 Calculate the local oscillator tuning range the frequency of t

```
1 //Example 9-1,Page No - 318
2
3 clear
4 clc
5
6 f1 =220*10^6
7 fm =224*10^6
8 IF1 = 10.7*10^6
9 IF = 1.5*10^6
10
11 IF2 =IF1+IF
12 tune_l =f1+IF1
13 tune_m = fm+IF1
14
15 IF1_imgl = tune_l+IF1
16 IF2_imgm = tune_m+IF1
17
18 printf('The local oscillatior tuning range is %.1f
19         to %.1f Mhz',tune_l/10^6,tune_m/10^6)
19 printf('\n Frequency of the second local oscillator
         is %.1f Mhz',IF2/10^6)
```

```
20 printf('\n First IF image range is %.1fto %.1f Mhz',
    IF1_imgl/10^6, IF2_imgm/10^6)
```

Scilab code Exa 9.2 Calculate the open circuit noise voltage

```
1 //Example 9-2,Page No - 324
2
3 clear
4 clc
5
6 R = 100*10^3
7 T = 273+25
8 B = 20*10^3
9 k = 1.38*10^-23
10
11 Vn=(4*k*T*B*R)^0.5
12
13 printf('The noise voltage across 100k resistor is %
    .2f microvolt ',Vn*10^6)
```

Scilab code Exa 9.3 What is the input thermal noise voltage of a receiver

```
1 // Example 9-3, Page No - 324
2
3 clear
4 clc
5
6 R=75
7 B=6*10^6
8 T = 29+273
9 k =1.38*10^-23
10 Vn = (4*k*T*B*R)^0.5
11
```

```
12 printf('The input thermal noise is %.2f microvolt',Vn
    *10^6)
```

Scilab code Exa 9.4 Calculate the average noise power of a device

```
1 //Example 9-4, Page No - 326
2
3 clear
4 clc
5
6 Tc=32.2
7 Tk=273+Tc
8 B =30*10^3
9 k =1.38*10^-23
10
11 Pn=k*Tk*B
12
13 printf('The average noise power is %.2f*10^-16 W',Pn
    *10^16)
```

Scilab code Exa 9.5 Calculate the noise factor and noise figure of the RF amplifier

```
1 //Example 9-5, page No- 329
2
3 clear
4 clc
5
6 SN_ip = 8
7 SN_op = 6
8
9 NR = SN_ip/SN_op
10 NF = 10*log10(NR)
11
```



```

12 printf('The noise factor is %.3f',NR)
13 printf('\n The noise figure is %.2f dB',NF)

```

Scilab code Exa 9.6 Calculate the input noise power the input signal power signal

```

1 //Example 9-6,Page No- 330
2
3 clear
4 clc
5
6 R= 75
7 T=31+273
8 k=1.38*106-23
9 B=6*106
10 Vs = 8.3*10-6
11 NF=2.8
12
13 Vn = (4*k*T*B*R)0.5
14 Pn = Vn2/R
15 Ps = Vs2/R
16 SN = (Ps*1012)/(Pn/1012)
17
18 SN_dB =10*log10(SN)
19 NR = 100.28
20 SN_op = SN/NR
21
22 Tn = 290*(NR-1)
23
24 printf('The input noise power is %.1f pW',Pn/1012)
25 printf('\n The input signal power is %.3f pW',Ps
    *1012)
26 printf('\n Signal to noise ratio in decibels %f',SN)
27 printf('\n The noise factor is %.1f',NR)
28 printf('\n Signal to noise ratio of the amplifier is
    %f',SN_op)

```

```
29 printf('\n The noise temperature of the amplifier %  
    .1 f K',Tn)
```

Chapter 10

Multiplexing and Demultiplexing

Scilab code Exa 10.1 Calculate the number of cahnnels carried by the cable TV serv

```
1 //Example 10-1,Page No - 368
2
3 clear
4 clc
5
6 BW_service = 860*10^6
7 BW_ch = 6*10^6
8
9 total_ch = BW_service/BW_ch
10
11 printf('Total number of channels are %d',total_ch)
```

Scilab code Exa 10.2 Calculate the number of available data channels number of bit

```
1 //Example 10-2, Page No -380
2
```

```
3 clear
4 clc
5
6 channels =16
7 sampling_rate= 3.5*10^3
8 w_len=6
9
10 available_ch =channels-1
11 bpf =channels*w_len
12 data_rate = sampling_rate * bpf
13
14 printf('Available channels are %d',available_ch)
15 printf('\n Bits Per Frame =%d',bpf)
16 printf('\n The serial data rate %.1f Khz',data_rate
    /10^3)
```

Chapter 11

The Transmission of Binary data in Communication Systems

Scilab code Exa 11.1 Calculate the time required to transmit single word single bi

```
1 //Example 11-1,Page No-392
2
3 clear
4 clc
5
6 t=0.0016
7 No_words=256
8 bits_word = 12
9
10 tword= t/No_words
11 tbit = tword/bits_word
12 bps =1/tbit
13
14 printf('The time duration of the word %.1f
        microsecond ',tword*10^8)
15 printf('\n The time duration of the one bit is %.4f
        microseconds ',tbit*10^8)
```

```
16 printf('\n The speed of transmission is %.1f kbps',  
    bps/10^5)
```

Scilab code Exa 11.2 Calculate the maximum theoretical data rate the maximum theor

```
1 //Example 11-2, Page no - 400  
2  
3 clear  
4 clc  
5  
6 B=12.5*10^3  
7 SN_dB= 25  
8  
9 C_th = 2*B  
10 SN=316.2  
11 C =B*3.32*log10(SN+1)  
12 N= 2^(C/(2*B))  
13  
14 printf('The maximum theorotical data rate is %.1f  
    kbps',C_th/10^3)  
15 printf('\n The maximum theorotical capacity of  
    channel is %.1f Kbps',C/10^3)  
16 printf('\n The number of levels needed to acheive  
    maximum speed are %d',N)
```

Scilab code Exa 11.3 Calculate the average number of errors that can be expected i

```
1 //Example 11-3,Page no - 430  
2  
3 clear  
4 clc  
5  
6 block =512
```

```
7 packets =8
8 BER = 2*10^-4
9
10 avg_errors = block*packets*8*BER
11
12 printf('Average number of errors are %.4f',
        avg_errors)
```

Chapter 12

Introduction to Networking and Local Area Network

Scilab code Exa 12.1 Calculate the number of interconnecting wires required to connect

```
1 //Example 12-1, page No - 448
2
3 clear
4 clc
5
6 N = 20
7
8 L = (N*(N-1))/2
9
10 printf('The number of interconnecting wires required
        are %d',L)
```

Scilab code Exa 12.2 Calculate the time required for the transmission of data on E

```
1 //Example 12-2, Page No - 474
2
```



```
3 clear
4 clc
5
6 block = 1500
7 ethernet = 10*10^6
8 token_ring = 16*10^6
9
10 t1_bit = 1/ethernet
11 t1_byte = 8*t1_bit
12 t1_1526 = 1526 *t1_byte
13 t2_bit = 1/token_ring
14 t2_byte = 8 * t2_bit
15 t2_1521 =1521*t2_byte
16
17 printf('Time required for the ethernet with the
    speed of 10Mbps is %.3f ns',t1_1526*10^6)
18 printf('\n Time required for the token ring format
    with the speed of 16 Mbps is %.3f ns',t2_1521
    *10^6)
```

Chapter 13

Transmission Lines

Scilab code Exa 13.1 1 Calculate the length of the cable considered to be a transm

```
1 //Example 13-1, Page No- 483
2
3 clear
4 clc
5
6 f= 450*10^6
7 lamda = 984/f
8 len =0.1*lamda
9
10 printf('%0.3f feet long conductors would be
    considered as the transmission line ',len*10^6)
```

Scilab code Exa 13.2 Calculate the physical length of the transmission line

```
1 //Example 13-2, Page No- 484
2
3 clear
4 clc
```

```

5
6 lamda = 2.19
7 len = (3/8)*lamda
8
9 printf('The pyhsical length of the transmission line
        %.2f feet ',len)

```

Scilab code Exa 13.3 Calculate the total attenuation and output power of the anten

```

1 //Example 13-3, Page No - 492
2
3 clear
4 clc
5
6 len = 165
7 attn_100ft = 5.3
8 pin = 100
9 attn_ft = 5.3/100
10
11 total_attn = attn_ft * len
12 pout = pin *0.1335
13
14 printf('The total attenuation of the cable is %.3f
        dB',total_attn)
15 printf('\n Output power is %.2f W',pout)

```

Scilab code Exa 13.4 Calculate the load impedance equivalent inductance time delay

```

1 //Example 13-4, Page No- 494
2
3 clear
4 clc
5

```

```

6 len =150
7 C =13.5
8 Z0 =93
9 f =2.5*10^6
10 attn_100ft =2.8
11
12 L =C*Z0^2
13 td =(L*C)^0.5
14 theta = ((360)*188.3)/(1/f)
15 attn_ft = attn_100ft/100
16 total_attn = attn_ft*150
17
18 printf('The load impedance required to terminate the
        the line\n to avoid the reflections is %d ohm',
        Z0)
19 printf('\n The equivalent inductance per feet is %.2
        f nH',L/10^3)
20 printf('\n The time delay introduced by the cable
        per feet is %.3f ns',td/10^3)
21 printf('\n The phase shift occurs in degrees for the
        2.5 Mhz sine wave is %.2f',theta/10^9)
22 printf('\n The total attenuation is %.1f dB',
        total_attn)

```

Scilab code Exa 13.5 Calculate the SWR reflection coefficient and value of resisti

```

1 //Example 13-5,Page No - 501
2
3 clear
4 clc
5
6 vmax= 52
7 vmin= 17
8 Z0 = 75
9

```

```

10 SWR = vmax/vmin
11 ref_coeff = (vmax-vmin)/(vmax+vmin)
12 Z11 = Z0*SWR
13 Z12 = Z0/SWR
14
15 printf('The standing wave ratio is %.2f',SWR)
16 printf('\n Reflection coefficient is %.2f',ref_coeff
    )
17 printf('\n The value of resistive load is %.2f or %
    .2f ohm',Z11,Z12)

```

Scilab code Exa 13.6 Calculate the output power of the cable

```

1 //Example 13-6,Page No- 503
2
3 clear
4 clc
5
6 SWR =3.05
7 ref_pwr =0.2562
8 pin =30
9
10 pout = pin -(pin*((SWR-1)/(SWR+1))^2)
11
12 printf('The output power of the cable is %.3f W',
    pout)

```

Scilab code Exa 13.7 Calculate the characteristics impedance of the microstrip tra

```

1 //Example 13-7,Page no - 508
2
3 clear
4 clc

```

```

5
6 C =4*10^-12
7 f =800*10^6
8 diele = 3.5
9 h = 0.0625
10 w = 0.13
11 t = 0.002
12
13 Z0 = 38.8*log(0.374/0.106)
14 Xc = 1/(6.28*f*C)
15
16 printf('The charecteristics impedance of the
    transmission line is %.1f ohm',Z0)
17 printf('\n The reactance of the capacitor is %.2f
    ohm',Xc)

```

Scilab code Exa 13.8 Calculate the length of the transmission line

```

1 //Example 13-8, Page No - 508
2
3 clear
4 clc
5
6 lamda = (984/800)
7 lamda_8 =lamda/8
8
9 len = lamda_8*12*(1/3.6^0.5)
10
11 printf('The length of the transmission line is %.4f'
    ,len)

```

Chapter 14

Antennas and Wave Propagation

Scilab code Exa 14.1 Calculate the length and radiation resistance for different a

```
1 //Example 14-1, page No - 544
2
3 clear
4 clc
5
6 f=310*10^6
7
8 len1 =(492*0.97)/f
9 len2 =(492/f)*0.8
10 len3 =(984/f)*0.73
11 z1 =120*log(35/2)
12 len4 =234/f
13 z2 = 73/2
14
15 printf('The length and radiation resistance of the
        dipole \n are %.2f feet and 73 ohm respectively',
        len1*10^6)
16 printf('\n\nThe length of the folded dipole are %.2f
        feet ',len2*10^6)
```

```

17 printf('\n\nThe length and radiation resistance of
    the bow tie antenna \n are %.1f feet and %.1f ohm
    respectively ',len3*10^6,z1)
18 printf('\n\nThe length and radiation resistance of
    the groun plane antenna \n are %.3f feet and %.1f
    ohmrespectively ',len4*10^6,z2)

```

Scilab code Exa 14.2 Calculate the transmission line loss and effective radiated p

```

1 //Example 14-2,page No - 553
2
3 clear
4 clc
5
6 gain=14
7 len=250
8 attn_100=3.6
9 f =220*10
10 pin =50
11 p =0.126
12
13 pout =pin*p
14 line_loss =pin-pout
15 pwr_ratio = 25.1
16 ERP = pwr_ratio*pout
17 printf('The transmission line loss is %.2f',
    line_loss)
18 printf('\n\nEffective raduated power is %.1f W',ERP)

```

Scilab code Exa 14.3 Calculate the length of the impedance matching section

```

1 //Example 14-3, Page No - 556
2

```



```

3 clear
4 clc
5
6 Z0 =50
7 Z1 =172
8 f =460*10^6
9 VF =0.86
10
11 len =(246/f)*VF
12 printf('The length of the impedance matching section
        \n needed for the Q section is %.2f feet ',len
        *10^6)

```

Scilab code Exa 14.4 Calculate the length of the impedance matching section

```

1 //Example 14-4,Page No - 557
2
3 clear
4 clc
5
6 f = 460*10^6
7 VF = 0.66
8 len = (246/f)*VF
9
10 printf('The length of impedance matching section is
        %.3f feet ',len*10^6)

```

Scilab code Exa 14.5 Calculate the maximum transmitting distance and received power

```

1 //Example 14-5,Page No - 567
2
3 clear
4 clc

```

```
5
6 ht =275
7 hr =60
8 f=224*10^6
9 pt=100
10 Gt = 26
11 Gr = 3.27
12
13 D =((2*ht)^0.5+(2*hr)^0.5)*1.61
14 lamda = 300/f
15 Pr = (pt*Gt*Gr*lamda^2)/(16*3.14^2*D^2)
16 printf('The maximmum transmitting distance is %.1f
    kilometer ',D)
17 printf('\n\n The received power is %.1f nW',Pr
    *10^15)
```

Chapter 16

Microwave Communication

Scilab code Exa 16.1 Calculate the required impedance of the microstrip and its length

```
1 //Example 16-1, Page No - 616
2
3 clear
4 clc
5
6 Zsrc =50
7 Zld =136
8 f =5800*10^6
9 Er =2.4
10 Zq =(Zsrc * Zld)^0.5
11 Vp =1/(Er)^0.5
12 lamda = 300/f
13 len = (lamda/4)*38.37*Vp
14
15 printf('The required impedance is %.2f ohm',Zq)
16 printf('\n\n The length of the microstrip %.2f
    inches ',len*10^6)
```

Scilab code Exa 16.2 Calculate the cutoff frequency and operating frequency of the

```

1 //Example 16-2,Page No-623
2
3 clear
4 clc
5
6 w=0.65
7 h=0.38
8
9 fco = 300/(2*((0.65*2.54)/100))
10 f =1.42*fco
11
12 printf('The cutoff frequency of the %.3f Ghz',fco
        /10^3)
13 printf('\n\n Operating frequency of the wavwguide is
        %.2f Ghz',f/10^3)

```

Scilab code Exa 16.3 Criterion for the operation of rectangular waveguide in the C

```

1 //Example 16-3,Page No- 623
2
3 clear
4 clc
5
6 printf('The c band is approximately 4 to 6 Ghz since
        a waveguide \n acts as a high pass filter with
        cut off frequency of \n 9.08 Ghz it will not pass
        c band signal')

```

Scilab code Exa 16.4 Calculate the lowest possible operating frequency gain and be

```

1 //Example 16-4, page No - 648
2
3 clear

```

```

4  clc
5
6  lamda1 =5
7  f2 = 15*10^9
8  D=1.524
9
10 f1=984/lamda1
11 lamda2 =300/f2
12 G = (6*(D/lamda2)^2)
13 B = 70/(D/lamda2)
14
15 printf('The lowest possible operating frequency is
        %.1f Mhz ',f1)
16 printf('\n\n The gain at 15 Ghz is %.1f ',G/10^12)
17 printf('\n\n The beam width at 15Ghz is %.2f degree'
        ,B*10^6)

```

Scilab code Exa 16.5 Calculate line of sight distance to aircraft and the altitude

```

1  //Example 16-5,Page No - 661
2
3  clear
4  clc
5
6  T = 9.2
7  theta = 20
8  sin20 = 0.342
9
10 D_nautical = T/12.36
11 D_statute =D_nautical*0.87
12 A = D_statute*0.342
13
14
15 printf('\nThe line of distance to the aircraft in \
        nthe statute miles %.3f ',D_statute)

```

```
16 printf('\n\nThe altitude of the aircraft is %.2f mi
    and in feet it is 1161.6',A)
```

Chapter 17

Satellite Communication

Scilab code Exa 17.1 Calculate the approximate azimuth and elevation setting of the

```
1 //Example 17-1,Page no - 678
2
3 clear
4 clc
5
6 stn_long = 95
7 stn_lat = 30
8 sat_long =121
9 rad_pos = 137
10 printf('The elevation setting for the antenna is 45
    degree')
11 azimuth = 360-rad_pos
12 printf('\n\nThe azimuth setting for the antenna is %d
    degree',azimuth)
```

Scilab code Exa 17.2 Calculate the uplink frequency and the maximum theoretical data

```
1 //Example 17-2,Page No -681
```

```

2
3 clear
4 clc
5
6 flo = 2*10^9
7 fd =3840*10^6
8 B =36*10^6
9
10 fu =fd+flo
11 C =2*B
12
13 printf('The uplink frequency is %.2f Ghz',fu/10^9)
14 printf('\n\nThe data rate is %d Mbps', C/10^6)

```

Scilab code Exa 17.3 Calculate local oscillator frequency to achieve the desired I

```

1 //Example 17-3,Page No - 691
2
3 clear
4 clc
5
6 fs = 4.08*10^9
7 fIF1 = 770*10^6
8 fIF2 = 140*10^6
9
10 flo1 = fs - fIF1
11 flo2 = fIF1 - fIF2
12
13 printf('The local oscillator frequency for first IF
    is %.1f Mhz',flo1/10^6)
14 printf('\n\n The local oscillator frequency for the
    second IF is %.1f Mhz',flo2/10^6)

```

Chapter 19

Optical Communication

Scilab code Exa 19.1 Calculate the critical angle of the fiber optic cable

```
1 //Example 19-1,page No - 760
2
3 clear
4 clc
5
6 NA = 0.29
7 critical_angle = sin (0.29)
8
9 printf('The critical angle is %.2f degree',
        critical_angle*(180/3.14))
```

Scilab code Exa 19.2 Calculate the bandwidth of the cable

```
1 //Example 19-2,Page No - 767
2
3 clear
4 clc
5
```

```

6 B_rating_Mhzkm =600*10^6
7 len_ft=500
8
9 bandwidth = B_rating_Mhzkm/(len_ft/3274)
10
11 printf('The bandwidth of the 500 feetr segment of
    the ccable is %.1f Mhz',bandwidth/10^6)

```

Scilab code Exa 19.3 Calculate the dispersion factor of the fiber optic cable

```

1 //Example 19-3,Page No - 780
2
3 clear
4 clc
5
6 R=43*10^6
7 D=1200/3274
8
9 d=1/(5*R*D)
10
11 printf('The dispersion factor is %.1f ns/km',d*10^9)

```
