

Scilab Textbook Companion for
Fundamentals Of Electronic Devices
by J. B. Gupta¹

Created by
Mohd. Arif
B.Tech
Computer Engineering
Uttarakhand Tech. university
College Teacher
Arshad Khan
Cross-Checked by
Lavitha Pereira

July 31, 2019

¹Funded by a grant from the National Mission on Education through ICT, <http://spoken-tutorial.org/NMEICT-Intro>. This Textbook Companion and Scilab codes written in it can be downloaded from the "Textbook Companion Project" section at the website <http://scilab.in>

Book Description

Title: Fundamentals Of Electronic Devices

Author: J. B. Gupta

Publisher: Katariya & Sons, New Delhi

Edition: 1

Year: 2009

ISBN: 978-93-80027-74-6

Scilab numbering policy used in this document and the relation to the above book.

Exa Example (Solved example)

Eqn Equation (Particular equation of the above book)

AP Appendix to Example(Scilab Code that is an Appednix to a particular Example of the above book)

For example, Exa 3.51 means solved example 3.51 of this book. Sec 2.3 means a scilab code whose theory is explained in Section 2.3 of the book.

Contents

List of Scilab Codes	4
1 Semiconductor materials and crystal properties	5
2 Energy Bands and Charge Carriers in Semiconductor	8
3 Excess Carriers in Semiconductors	20
4 Junction Properties	25
5 Junction Properties Continued	38
6 Bipolar Junction Transistors	42
7 Field Effect Transistors	52
8 Photonic Devices	58

List of Scilab Codes

Exa 1.3	Calculate Density of Copper Crystal	5
Exa 1.4	Obtain volume density of Si atoms	6
Exa 1.5	Calculate surface density of atoms	6
Exa 1.6	Determine Interplanar Distance	7
Exa 1.7	Determine Wavelength of X rays	7
Exa 2.1	Calculate the velocity of electron at fermi level	8
Exa 2.2	Determine Drift Velocity of Electrons	8
Exa 2.3	Calculate magnitude of current	9
Exa 2.4	Find electron and hole densities	9
Exa 2.5	Calculate concentrations in semiconductor	10
Exa 2.6	Find ratio of electron to hole concentration	11
Exa 2.7	Calculate relaxation time resistivity and velocity of electron	11
Exa 2.8	Find conductivity and resistivity	12
Exa 2.9	Calculate density of electron	13
Exa 2.10	Find conductivity of Si	13
Exa 2.11	Find conductivity of intrinsic Ge	14
Exa 2.12	Find drift velocity of electron and hole Conductivity and current	14
Exa 2.13	Find diffusion coefficient of electron and hole	15
Exa 2.14	Find mobility and density of charge carriers	16
Exa 2.15	Determine current density	16
Exa 2.16	Calculate Hall coefficients	17
Exa 2.17	Find magnitude of hall voltage	17
Exa 2.18	Determine mobility of holes	18
Exa 2.19	Determine Hall Voltage	18
Exa 2.20	Calculate Hall angle	19
Exa 3.2	Find minimum Energy	20

Exa 3.3	Calculate work function	20
Exa 3.4	Determine power absorbed and rate of excess thermal energy	21
Exa 3.5	Determine electron transit time and photo-conductor gain	22
Exa 3.6	Determine current through diode	22
Exa 3.7	Find forward voltage	23
Exa 3.8	Find reverse saturation current density	23
Exa 4.2	Calculate electron and hole concentration at thermal equilibrium	25
Exa 4.3	Calculate electron and hole concentration at thermal equilibrium	25
Exa 4.4	determine built in potential barrier	26
Exa 4.5	Obtain value of contact potential	26
Exa 4.6	Determine space charge width and electric field	27
Exa 4.7	Obtain value of contact potential	28
Exa 4.8	Calculate height of potential barrier	28
Exa 4.9	Find current in the circuit	29
Exa 4.10	Determine voltage V_A in the circuit	29
Exa 4.12	Determine temperature coefficients	30
Exa 4.13	Find output voltage and current through Zener diode	31
Exa 4.14	Find maximum and minimum values of zener diode current	31
Exa 4.15	Design a regulator	32
Exa 4.16	Determine V_L I_Z and P_Z	33
Exa 4.17	Comment on operation of circuit	33
Exa 4.18	Find voltage drop across the resistance	34
Exa 4.19	Find R_i so that V_L remain 12V	35
Exa 4.20	Determine range of R_L and I_L	36
Exa 5.1	Estimate junction width	38
Exa 5.3	Find new position of fermi level	39
Exa 5.4	Calculate height of potential barrier	39
Exa 5.5	Find electron and hole concentration	40
Exa 5.6	Determine junction capacitance	41
Exa 6.1	Determine emitter current	42
Exa 6.2	Determine emitter current amplification factor and gain factor	42

Exa 6.3	Determine emitter current and collector current	43
Exa 6.4	Determine collector current	43
Exa 6.5	Calculate dynamic input resistance	44
Exa 6.6	Determine base and collector current	44
Exa 6.7	Determine current gain and base current	45
Exa 6.8	Determine base current	45
Exa 6.9	Determine base current	46
Exa 6.10	Determine collector emitter voltage and base current	46
Exa 6.11	Determine collector current	47
Exa 6.12	Calculate dynamic input resistance	47
Exa 6.13	Calculate dynamic output resistance	48
Exa 6.14	Determine operating point	48
Exa 6.15	Find VCE at cut off point	49
Exa 6.16	Determine VC and VB	49
Exa 6.17	Find IB and IC	50
Exa 7.1	Determine resistance between gate and source	52
Exa 7.2	Calculate AC drain resistance	52
Exa 7.3	Determine Transconductance	53
Exa 7.4	Calculate VGS	53
Exa 7.5	Determine minimum value of VDS	54
Exa 7.6	Findd values of ID gmo and gm	54
Exa 7.7	Findd values of ID and gm	55
Exa 7.8	Find value of VGS and gm	55
Exa 7.9	Sketch the transfer Characteristics	56
Exa 7.10	Determine Drain current	56
Exa 8.1	Determine steady state photo current density	58
Exa 8.2	Determine photo current density	59
Exa 8.3	Determine open circuit voltage	59
Exa 8.4	Determine approximate no of solar cell required	60

Chapter 1

Semiconductor materials and crystal properties

Scilab code Exa 1.3 Calculate Density of Copper Crystal

```
1 //Exa 1.3
2 clc;
3 clear;
4 close;
5 //given data
6 r=1.278;//in Angstrum
7 AtomicWeight=63.5;//constant
8 AvogadroNo=6.023*10^23;//constant
9 //For FCC structure a=4*r/sqrt(2)
10 a=4*r*10^-10/sqrt(2);//in meter
11 V=a^3;//in meter^3
12 //mass of one atom = m
13 m=AtomicWeight/AvogadroNo;//in gm
14 m=m/1000;//in Kg
15 n=4;// no. of atoms per unit cell for FCC structure
16 rho=m*n/V;//in Kg/m^3
17 disp(rho,"Density of crystal in Kg/m^3: ");
```

Scilab code Exa 1.4 Obtain volume density of Si atoms

```
1 //Exa 1.4
2 clc;
3 clear;
4 close;
5 //given data
6 n=4; // no. of atoms per unit cell of silicon
7 AtomicWeight=28; //constant
8 AvogadroNo=6.021*10^23; //constant
9 m=AtomicWeight/AvogadroNo; //in gm
10 m=m/1000; //in Kg
11 a=5.3; //lattice constant in Angstrum
12 a=a*10^-10; //in meter
13 V=a^3; //in meter^3
14 rho=m*n/V; //in Kg/m^3
15 disp(rho,"Density of silicon crystal in Kg/m^3: ");
```

Scilab code Exa 1.5 Calculate surface density of atoms

```
1 //Exa 1.5
2 clc;
3 clear;
4 close;
5 //given data
6 a=4.75; //lattice constant in Angstrum
7 a=a*10^-10; //in meter
8 disp("Surface density in FCC on (111) Plane : dp =
      2.31/a^2");
9 dp=2.31/a^2; //in atom/m^2
10 dp=dp/10^6; //in atom/mm^2
```

```
11 disp(dp," Surface density in FCC on (111) Plane in
    atoms/mm^2: ");
```

Scilab code Exa 1.6 Determine Interplanar Distance

```
1 //Exa 1.6
2 clc;
3 clear;
4 close;
5 //given data
6 lambda=1.539;//in Angstrom
7 theta=22.5;//in degree
8 n=1;//order unitless
9 d=n*lambda/(2*sin(theta*pi/180));//in Angstrom
10 disp(d,"Interpolar distance in Angstrom : ")
```

Scilab code Exa 1.7 Determine Wavelength of X rays

```
1 //Exa 1.7
2 clc;
3 clear;
4 close;
5 //given data
6
7 theta=16.8/2;//in degree
8 n=2;//order unitless
9 d=0.4;//in nm
10 lambda=(2*d*sin(theta*pi/180))/n;//in Angstrom
11 disp(lambda,"wavelength of X-rays in Angstrom : ");
12 //Note: Ans in the book is not correct
```

Chapter 2

Energy Bands and Charge Carriers in Semiconductor

Scilab code Exa 2.1 Calculate the velocity of electron at fermi level

```
1 //Exa 2.1
2 clc;
3 clear;
4 close;
5 //given data
6 E=2.1;//in eV
7 E=E*1.602*10^-19;//in Joule
8 m=9.107*10^-31;//in Kg
9 //Formula : E= (m*v^2)/2
10 v=sqrt(2*E/m);//in m/s
11 disp(v,"Velocity of electron at fermi level in m/s :
      ");
```

Scilab code Exa 2.2 Determine Drift Velocity of Electrons

```
1 //Exa 2.2
```

```

2  clc;
3  clear;
4  close;
5  //given data
6  J=2.4; //in A/mm^2
7  J=J*10^6; //in A/m^2
8  n=5*10^28; //electrons/m^3
9  e=1.6*10^-19; //constant
10 //Formula : J=e*n*v
11 v=J/(e*n); //in m/s
12 disp(v*10^3," Velocity of electron at fermi level in
      mm/s : ");

```

Scilab code Exa 2.3 Calculate magnitude of current

```

1  //Exa 2.3
2  clc;
3  clear;
4  close;
5  //given data
6  n=10^24; //electrons/m^3
7  e=1.6*10^-19; //constant
8  v=1.5*10^-2; //in m/s
9  A=1; //in cm^2
10 A=1*10^-4; //in m^2
11 I=e*n*v*A; //in Ampere
12 disp(I," Magnitude of current in Ampere : ");

```

Scilab code Exa 2.4 Find electron and hole densities

```

1  //Exa 2.4
2  clc;
3  clear;

```

```

4 close;
5 //given data
6 ni=2.5*10^13;//in atoms/cm^3
7 rho=0.039;//in ohm-cm
8 SIGMA_n=1/rho;//in (ohm-cm)^-1
9 e=1.6*10^-19;//constant
10 MUE=3600;//in cm^2/V-s
11 //formula : SIGMA_n=n*e*MUE=Nd*e*MUE
12 Nd=SIGMA_n/(e*MUE);//in atoms/cm^3
13 n=Nd;//in atoms/cm^3
14 p=ni^2/n;//in atoms/cm^3
15 disp(n,"Electron density in atoms/cm^3 : ");
16 disp(p,"Hole density in atoms/cm^3 : ");

```

Scilab code Exa 2.5 Calculate concentrations in semiconductor

```

1 //Exa 2.5
2 clc;
3 clear;
4 close;
5 //given data
6 DonorImpurity=1/10^6;;//impurity per atom
7 SiAtomCon=5*10^22;//in cm^-3
8 ni=1.45*10^10;//in cm^-3
9 MUE=1300;//in cm^2/V-s
10 e=1.6*10^-19;//constant
11 //part (i)
12 Nd=SiAtomCon*DonorImpurity;//in cm^-3
13 disp(Nd,"Donor atom concentration in cm^-3 : ");
14 //part (ii)
15 n=Nd;//in cm^-3
16 disp(n,"Mobile electron concentration in cm^-3: ");
17 //part (iii)
18 p=ni^2/Nd;//in cm^-3
19 disp(p,"Hole concentration in cm^-3 : ");

```

```

20 //part (iv)
21 SIGMA=n*e*MUe;//in (ohm-cm)^-1
22 disp(SIGMA,"Conductivity of doped silicon sample in
      (ohm-cm)^-1 : ");
23 //part (v)
24 rho=1/SIGMA;//in ohm-cm
25 l=0.5;//in cm
26 A=(50*10^-4)^2;//in cm^2
27 R=rho*l/A;//in ohm
28 disp(rho,"Resistivity in ohm-cm : ");
29 disp(R,"Resistance in ohm : ")

```

Scilab code Exa 2.6 Find ratio of electron to hole concentration

```

1 //Exa 2.6
2 clc;
3 clear;
4 close;
5 //given data
6 ni=1.4*10^18;//in atoms/m^3
7 Nd=1.4*10^24;//in atoms/m^3
8 n=Nd;//in atoms/m^3
9 p=ni^2/n;//in atoms/m^3
10 ratio=n/p;//unitless
11 disp(p,"Concentration of holes in per m^3 : ");
12 disp(ratio,"Ratio of electron to hole concentration
      : ");

```

Scilab code Exa 2.7 Calculate relaxation time resistivity and velocity of electron

```

1 //Exa 2.7
2 clc;
3 clear;

```

```

4 close;
5 //given data
6 Ef=5.5; //in eV
7 MUE=7.04*10^-3; //in m^2/V-s
8 n=5.8*10^28; //in m^-3
9 e=1.6*10^-19; //constant
10 m=9.1*10^-31; //in Kg
11 //part (i)
12 tau=MUE*m/e; //in sec
13 disp(tau,"Relaxation time in sec : ");
14 rho=1/(n*e*MUE); //in ohm-m
15 disp(rho,"Resistivity of conductor in ohm-m : ")
16 vF=sqrt(2*Ef*1.6*10^-19/m);
17 disp(vF,"velocity of electron with fermi energy in m
/s : ");

```

Scilab code Exa 2.8 Find conductivity and resistivity

```

1 //Exa 2.8
2 clc;
3 clear;
4 close;
5 //given data
6 ni=2.5*10^13; //in cm^-3
7 e=1.6*10^-19; //in coulamb
8 MUh=1800; //in cm^2/V-s
9 MUE=3800; //in cm^2/V-s
10 SIGMAi=ni*e*(MUE+MUh); //in (ohm-cm)^-1
11 RHOi=1/SIGMAi; //in ohm-cm
12 disp(SIGMAi,"Intrinsic conductivity in (ohm-cm)^-1 :
");
13 disp(RHOi,"Intrinsic resistivity in ohm-cm : ");

```

Scilab code Exa 2.9 Calculate density of electron

```
1 //Exa 2.9
2 clc;
3 clear;
4 close;
5 //given data
6 SIGMAi=2.12766; //in S/m
7 RHOi=0.47; //in ohm-m
8 MUh=0.19; //in m2/V-s
9 MUE=0.39; //in m2/V-s
10 e=1.6*10-19; //in coulamb
11 //Formula : SIGMAi=ni*e*(MUE+MUh)
12 ni=SIGMAi/(e*(MUE+MUh)); //in m-3
13 E=104; //in V/m
14 vn=MUE*E; //in m/s
15 vh=MUh*E; //in m/s
16 disp(ni,"Density of electron in intrinsic material
    in m-3 : ");
17 disp(vn,"Drift velocity for electrons in m/s : ");
18 disp(vh,"Drift velocity for holes in m/s : ");
```

Scilab code Exa 2.10 Find conductivity of Si

```
1 //Exa 2.10
2 clc;
3 clear;
4 close;
5 //given data
6 ni=1.5*1010; //in cm-3
7 e=1.6*10-19; //in coulamb
8 MUh=450; //in cm2/V-s
9 MUE=1300; //in cm2/V-s
10 SIGMAi=ni*e*(MUE+MUh); //in (ohm-cm)-1
11 disp(SIGMAi,"Conductivity of silicon(intrinsic) in (
```



```

    ohm-cm)^-1 ");
12 Na=10^18; //in cm^-1
13 SIGMAP=e*Na*MUh; //in (ohm-cm)^-1
14 disp(SIGMAP,"Conductivity of resulting P-type si
    semiconductor in (ohm-cm)^-1 : ");

```

Scilab code Exa 2.11 Find conductivity of intrinsic Ge

```

1 //Exa 2.11
2 clc;
3 clear;
4 close;
5 //given data
6 ni=2.5*10^13; //in cm^-3
7 e=1.6*10^-19; //in coulamb
8 MUh=1800; //in cm^2/V-s
9 MUE=3800; //in cm^2/V-s
10 SIGMAi=ni*e*(MUE+MUh); //in (ohm-cm)^-1
11 GeAtoms=4.41*10^22; //in cm^-1
12 DonorImpurity=1/10^7; //in per Ge Atom
13 Nd=4.41*10^22*DonorImpurity; //in cm^-1
14 n=Nd; //in cm^-1
15 p=ni^2/Nd; //in cm^-3
16 SIGMAN=e*Nd*MUE; //in (ohm-cm)^-1
17 disp(SIGMAi,"Conductivity of Ge(intrinsic) in (ohm-
    cm)^-1 ");
18 disp(SIGMAN,"Conductivity of resulting N-type Ge
    semiconductor in (ohm-cm)^-1 : ");

```

Scilab code Exa 2.12 Find drift velocity of electron and hole Conductivity and cur

```

1 //Exa 2.12
2 clc;

```

```

3 clear;
4 close;
5 //given data
6 e=1.6*10^-19;//in coulomb
7 MUh=0.18;//in m^2/V-s
8 MUE=0.38;//in m^2/V-s
9 V=10;//in Volts
10 l=25;//in mm
11 w=4;//in mm
12 t=1.5;//in mm
13 E=V/(1*10^-3);//in
14 //part (i)
15 ve=MUE*E;//in m/s
16 vh=MUH*E;//in m/s
17 disp(ve," Drift velocity for electrons in m/s : ");
18 disp(vh," Drift velocity for holes in m/s : ");
19
20 ni=2.5*10^19;//in m^-3
21 //part (ii)
22 SIGMAi=ni*e*(MUE+MUH);//in (ohm-m)^-1
23 disp(SIGMAi," Conductivity of Ge(intrinsic) in (ohm-m
    )^-1 ");
24 //part (iii)
25 I=SIGMAi*E*w*10^-3*t*10^-3;//in Ampere
26 disp(I*10^3," Total current in mili ampere : ");

```

Scilab code Exa 2.13 Find diffusion coefficient of electron and hole

```

1 //Exa 2.13
2 clc;
3 clear;
4 close;
5 //given data
6 e=1.6*10^-19;//in coulomb
7 T=300;//in Kelvin

```

```

8 MUh=1700; //in cm^2/V-s
9 MUE=3600; //in cm^2/V-s
10 k=1.38*10^-23; //in J/K
11 De=MUE*k*T/e; //in cm^2/s
12 Dh=MUh*k*T/e; //in cm^2/s
13 disp(De," Diffusion constant of electron(in cm^2/s) :
      ");
14 disp(Dh," Diffusion constant of hole(in cm^2/s) : ");

```

Scilab code Exa 2.14 Find mobility and density of charge carriers

```

1 //Exa 2.14
2 clc;
3 clear;
4 close;
5 //given data
6 e=1.6*10^-19; //in coulomb
7 resistivity=9*10^-3; //in ohm-m
8 RH=3.6*10^-4; //in m^3-coulomb^-1
9 SIGMA=1/resistivity; //in (ohm-m)^-1
10 rho=1/RH; //in coulomb/m^3
11 n=rho/e; //in m^-3
12 disp(n," Density of charge carriers in m^-3 : ");
13 MU=SIGMA*RH; //in m^2/V-s
14 disp(MU," Mobility in m^2/V-s : ");

```

Scilab code Exa 2.15 Determine current density

```

1 //Exa 2.15
2 clc;
3 clear;
4 close;
5 //given data

```

```

6 e=1.6*10^-19; //in coulomb
7 E=100; //in V/m
8 RH=0.0145; //in m^3-coulamb^-1
9 MUn=0.36; //in m^2/V-s
10 J=MUn*E/RH; //in A/m^2
11 disp(J,"Current density in A/m^2 : ");

```

Scilab code Exa 2.16 Calculate Hall coefficients

```

1 //Exa 2.16
2 clc;
3 clear;
4 close;
5 //given data
6 e=1.6*10^-19; //in coulomb
7 n=2.05*10^22; //in m^-3
8 RH=1/(n*e); //in m^3-coulamb^-1
9 disp(RH,"Hall coefficient in m^3-coulamb^-1 : ");

```

Scilab code Exa 2.17 Find magnitude of hall voltage

```

1 //Exa 2.17
2 clc;
3 clear;
4 close;
5 //given data
6 e=1.6*10^-19; //in coulomb
7 ND=10^17; //in cm^-3
8 Bz=0.1; //in Wb/m^2
9 w=4; //in mm
10 d=4; //in mm
11 Ex=5; //in V/cm
12 MUE=3800; //in cm^2/V-s

```

```

13 v=MUe*Ex; //in cm/s
14 v=v*10^-2; //in m/s
15 VH=Bz*v*d; //in mV
16 disp(VH,"Magnitude of hall voltage in mV : ");

```

Scilab code Exa 2.18 Determine mobility of holes

```

1 //Exa 2.18
2 clc;
3 clear;
4 close;
5 //given data
6 e=1.6*10^-19; //in coulomb
7 w=3; //in mm
8 d=3; //in mm
9 rho=200; //in Kohm-cm
10 rho=rho*10^3*10^-2; //in ohm-m
11 VH=50; //in mV
12 VH=VH*10^-3; //in Volts
13 I=10; //in uA
14 I=I*10^-6; //in Ampere
15 Bz=0.1; //in Wb/m^2
16 RH=VH*w*10^-3/(Bz*I)
17 MUh=RH/rho; //in m^2/V-s
18 disp(MUh,"Mobility of holes in p-type Si bar in m^2/
    V-s : ");

```

Scilab code Exa 2.19 Determine Hall Voltage

```

1 //Exa 2.19
2 clc;
3 clear;
4 close;

```

```

5 //given data
6 e=1.6*10^-19;//in coulamb
7 ND=10^21;//in m^-3
8 Bz=0.2;//in T
9 d=4;//in mm
10 d=d*10^-3;//in meter
11 J=600;//in A/m^2
12 n=ND;//in m^-3
13 //formula : VH*w/(B*I)=1/(n*e)
14 VH=Bz*J*d/(n*e);//in V
15 disp(VH*10^3,"Magnitude of hall voltage in mV : ");

```

Scilab code Exa 2.20 Calculate Hall angle

```

1 //Exa 2.20
2 clc;
3 clear;
4 close;
5 //given data
6 e=1.6*10^-19;//in coulamb
7 rho=0.00912;//in ohm-m
8 B=0.48;//in Wb/m^2
9 RH=3.55*10^-4;//in m^3-coulamb^-1
10 SIGMA=1/rho;//in (ohm-m)^-1
11 THETAh=atand(SIGMA*B*RH);//in Degree
12 disp(THETAh,"Hall angle in degree : ");

```

Chapter 3

Excess Carriers in Semiconductors

Scilab code Exa 3.2 Find minimum Energy

```
1 //Exa 3.2
2 clc;
3 clear;
4 close;
5 //given data
6 lambda=6000;//in Angstrum
7 h=6.6*10^(-34);//Planks constant
8 c=3*10^8;//speed of light in m/s
9 e=1.602*10^(-19);//Constant
10 phi=c*h/(e*lambda*10^(-10));
11 disp(phi,"Minimum required energy in eV is :");
12 //Note : Ans in the book is n ot correct
```

Scilab code Exa 3.3 Calculate work function

```
1 //Exa 3.3
```

```

2  clc;
3  clear;
4  close;
5  //given data
6  Emax=2.5; //maximum energy of emitted electrons in eV
7  lambda=2537; //in Angstrum
8  EeV=12400/lambda; //in eV
9  disp(EeV,"The eV equivalent of the energy of
        incident photon : ");
10 phi=EeV-Emax; //in eV
11 disp(phi,"Work function of the cathode material is "
        );

```

Scilab code Exa 3.4 Determine power absorbed and rate of excess thermal energy

```

1  //Exa 3.4
2  clc;
3  clear;
4  close;
5  //given data
6  t=0.46*10^-6; //in meters
7  hf=2; //in ev
8  Pin=10; //in mW
9  alpha=50000; // in per cm
10 e=1.6*10^-19; //constant
11 Io=10^-2; //in mW
12 It=Io*e^(-alpha*t); //in mW
13 //Part (i)
14 disp("Thus power absorbed =  $10-1 = 9$  mW or 0.009 J/s
        ");
15 disp((2-1.43)/2,"The fraction of each photon energy
        unit which is converted into heat");
16 //Part (ii)
17 disp((2-1.43)/2)*0.009,"Energy converted into heat
        in J/s:");

```



```
18 //Part (iii)
19 disp(0.009/(e*2),"Number of photons per second given
    off from recombination events :");
```

Scilab code Exa 3.5 Determine electron transit time and photoconductor gain

```
1 //Exa 3.5
2 clc;
3 clear;
4 close;
5 //given data
6 L=100;//in uM
7 A=10^-7;//in cm^2
8 th=10^-6;//in sec
9 V=12;//in Volts
10 ue=0.13;//in m^2/V-s
11 uh=0.05;//in m^2/V-s
12 E=V/(L*10^-6);//in V/m
13 tn=(L*10^-6)/(ue*E);
14 disp(tn,"Electron transit time in sec is ");
15 Gain=(1+uh/ue)*(th/tn);
16 disp(Gain,"Photoconductor gain is ");
```

Scilab code Exa 3.6 Determine current through diode

```
1 //Exa 3.6
2 clc;
3 clear;
4 close;
5 //given datex
6 Io=0.15;//in uA
7 V=0.12;//in mVolt
8 Vt=26;//in mVolt
```

```

9 I=Io*10^-6*(exp(V/(Vt*10^-3))-1); //in A
10 disp(I*10^6,"Current flowing through diode in uA is
    ");

```

Scilab code Exa 3.7 Find forward voltage

```

1 //Exa 3.7
2 clc;
3 clear;
4 close;
5 //given data
6 Io=2.5; //in uA
7 I=10; //in mA
8 Vt=26; //in mVolt
9 n=2; //for silicon
10 V=n*Vt*10^-3*log((I*10^-3)/(Io*10^-6))
11 disp(V,"Forward voltage in volts is ");

```

Scilab code Exa 3.8 Find reverse saturation current density

```

1 //Exa 3.8
2 clc;
3 clear;
4 close;
5 //given data
6 ND=10^21; //in m^-3
7 NA=10^22; //in m^-3
8 De=3.4*10^-3; //in m^2-s^-1
9 Dh=1.2*10^-3; //in m^2-s^-1
10 Le=7.1*10^-4; //in meters
11 Lh=3.5*10^-4; //in meters
12 ni=1.6*10^16; //in m^-3
13 e=1.602*10^-19; //constant

```

```
14 IoA=e*ni^2*(Dh/(Lh*ND)+De/(Le*NA));
15 disp(IoA*10^6,"Reverse saturation current density in
    uA/m2 is ")
```

Chapter 4

Junction Properties

Scilab code Exa 4.2 Calculate electron and hole concentration at thermal equilibrium

```
1 //Exa4.2
2 clc;
3 clear;
4 close;
5 //given data
6 T=300;//in Kelvin
7 ND=10^16;//in cm^-3
8 NA=0;//in cm^-3
9 ni=1.5*10^10;//in cm^-3
10 no=ND/2+sqrt((ND/2)^2+ni^2);//in cm^-3
11 po=ni^2/no;//in cm^-3
12 disp(no,"Majority carrier electron concentration in
        cm^-3 : ");
13 disp(po,"Minority carrier hole concentration in cm
        ^-3 : ");
```

Scilab code Exa 4.3 Calculate electron and hole concentration at thermal equilibrium

```

1 //Exa4.3
2 clc;
3 clear;
4 close;
5 //given data
6 T=300;//in Kelvin
7 ND=3*10^15;//in cm^-3
8 NA=10^16;//in cm^-3
9 ni=1.6*10^10;//in cm^-3
10 po=(NA-ND)/2+sqrt(((NA-ND)/2)^2+ni^2);//in cm^-3
11 no=ni^2/po;//in cm^-3
12 disp(po,"Majority carrier hole concentration in cm
    ^-3 : ");
13 disp(no,"Minority carrier electron concentration in
    cm^-3 : ");

```

Scilab code Exa 4.4 determine built in potential barrier

```

1 //Exa4.4
2 clc;
3 clear;
4 close;
5 //given data
6 T=300;//in Kelvin
7 ND=10^15;//in cm^-3
8 NA=10^18;//in cm^-3
9 ni=1.5*10^10;//in cm^-3
10 VT=T/11600;//in Volts
11 Vbi=VT*log(NA*ND/ni^2);//in Volts
12 disp(Vbi,"Built in potential barrier in volts : ");

```

Scilab code Exa 4.5 Obtain value of contact potential

```

1 //Exa4.5
2 clc;
3 clear;
4 close;
5 //given data
6 T=300; //in Kelvin
7 ND=10^21; //in m^-3
8 NA=10^21; //in m^-3
9 ni=1.5*10^16; //in m^-3
10 VT=T/11600; //in Volts
11 Vo=VT*log(NA*ND/ni^2); //in Volts
12 disp(Vo,"Contact potential in volts : ");

```

Scilab code Exa 4.6 Determine space charge width and electric field

```

1 //Exa4.6
2 clc;
3 clear;
4 close;
5 //given data
6 T=300; //in Kelvin
7 ND=10^15; //in cm^-3
8 NA=10^16; //in cm^-3
9 ni=1.5*10^10; //in cm^-3
10 VT=T/11600; //in Volts
11 e=1.6*10^-19; //in Coulomb
12 epsilon=11.7*8.854*10^-14; //constant
13 Vbi=VT*log(NA*ND/ni^2); //in Volts
14 SCW=sqrt((2*epsilon*Vbi/e)*(NA+ND)/(NA*ND)); //in cm
15 SCW=SCW*10^4; //in uMeter
16 disp(SCW,"Space charge width in uMeters : ");
17 xn=0.864; //in uM
18 xp=0.086; //in uM
19 Emax=-e*ND*xn/epsilon; //in V/cm
20 disp(Emax,"At metallurgical junction , i.e for x=0

```

```
    the electric field is peak i.e. Emax in volts : ”
    );
21 //Note : Ans in the book is wrong
```

Scilab code Exa 4.7 Obtain value of contact potential

```
1 //Exa4.7
2 clc;
3 clear;
4 close;
5 //given data
6 T=300;//in Kelvin
7 ND=10^21;//in m^-3
8 NA=10^21;//in m^-3
9 ni=1.5*10^16;//in m^-3
10 VT=T/11600;//in Volts
11 Vo=VT*log(NA*ND/ni^2);//in Volts
12 disp(Vo,"Contact potential in volts : ");
```

Scilab code Exa 4.8 Calculate height of potential barrier

```
1 //Exa4.8
2 clc;
3 clear;
4 close;
5 //given data
6 T=300;//in Kelvin
7 ND=8*10^14;//in cm^-3
8 NA=8*10^14;//in cm^-3
9 ni=2*10^13;//in cm^-3
10 k=8.61*10^-5;//in eV/K
11 Vo=k*T*log(NA*ND/ni^2);//in Volts
12 disp(Vo,"Contact potential in volts : ");
```

Scilab code Exa 4.9 Find current in the circuit

```
1 //Exa4.9
2 clc;
3 clear;
4 close;
5 //In given circuit :
6 V=5;//in volts
7 Vo=0.7;//in Volts
8 R=100;//in Kohm
9 disp("Since diode is silicon one, and the barrier
      potential for Si diode is 0.7 volt , Vo = 0.7
      volts ");
10 disp("This barrier potential acts in opposite
      direction to the applied voltage. The diode
      forward resistance is being assumed to be zero.")
      ;
11 I=(V-Vo)/R;//in Ampere
12 disp(I*1000,"Current flowing through the circuit in
      Amperes :")
```

Scilab code Exa 4.10 Determine voltage VA in the circuit

```
1 //Exa4.10
2 clc;
3 clear;
4 close;
5 //In given circuit :
6 V=15;//in volts
7 Vo=0.7;//in Volts
8 R=7;//in Kohm
```



```

9 I=(V-2*Vo)/R
10 disp("Since diode is silicon one, and the barrier
    potential for Si diode is 0.7 volt, Vo = 0.7
    volts ");
11 disp("This barrier potential acts in opposite
    direction to the applied voltage. The diode
    forward resistance is being assumed to be zero.")
    ;
12 I=(V-2*Vo)/R; //in mAmpere
13 disp("Barrier potential of Si diode, Vo = 0.7 Volts"
    );
14 disp("Potential VA = Voltage drop across 7 Kohm
    resistor");
15 VA=I*R; //in Volts
16 disp(VA,"Voltagee VA in volts : ");

```

Scilab code Exa 4.12 Determine temperature coefficients

```

1 //Exa4.12
2 clc;
3 clear;
4 close;
5 //given data
6 Vz=5; //in volts
7 to=25; //in degree centigrade
8 t=100; //in degree centigrade
9 Vdrop=4.8; //in Volts
10 delVz=Vdrop-Vz; //in Volts
11 delT=t-to; //in degree centigrade
12 TempCoeff=delVz*100/(Vz*delT);
13 disp(TempCoeff,"Temperature coefficient f zener
    diode in % : ");

```

Scilab code Exa 4.13 Find output voltage and current through Zener diode

```
1 //Exa4.13
2 clc;
3 clear;
4 close;
5 //given data
6 Vz=8;//in volts
7 VS=12;//in volts
8 Vout=8;//in volts
9 RL=10;//in Kohm
10 Rs=5;//in Kohm
11 //part (a)
12 disp("Output voltage will be equal to Vz i.e "+
      string(Vz)+" Volts");
13 //part (b)
14 Vrs=VS-Vout;//in volts
15 disp(Vrs,"Voltage across Rs in volts : ");
16 IL=Vout/RL;//in mAmpere
17 Is=(VS-Vout)/Rs;//in mAmpere
18 Iz=Is-IL;//in mAmpere
19 disp(Iz,"Current through zener diode in mA : ");
```

Scilab code Exa 4.14 Find maximum and minimum values of zener diode current

```
1 //Exa4.14
2 clc;
3 clear;
4 close;
5 //given data
6 Vz=50;//in volts
7 VSmax=120;//in volts
8 VSmin=80;//in volts
9 RL=10;//in Kohm
10 Rs=5;//in Kohm
```

```

11 Vout=Vz;//in Volts
12 disp("Output voltage will be equal to Vz i.e "+
      string(Vz)+" Volts");
13 IL=Vout/RL;//in mAmpere
14 disp("The zener current will be maximum when input
      voltage is maximum i.e. 120V.");
15 ISmax=(VSmax-Vout)/Rs;//in mAmpere
16 Izmax=ISmax-IL;//in mA
17 disp(Izmax,"Maximum zener diode current in mA : ");
18 disp("The zener current will be minimum when input
      voltage is minimum i.e. 80V.");
19 Ismin=(VSmin-Vout)/Rs;//in mAmpere
20 Izmin=Ismin-IL;//in mA
21 disp(Izmin,"Minimum zener diode current in mA : ");

```

Scilab code Exa 4.15 Design a regulator

```

1 //Exa4.15
2 clc;
3 clear;
4 close;
5 //given data
6 Vz=15;//in volts
7 Izk=6;//in mA
8 Vout=15;//in Volts
9 Vs=20;//in Volts
10 ILmin=10;//in mA
11 ILmax=20;//in mA
12 disp("the zener current will be minimum i.e. Izk = 6
      mA when load current is maximum i.e. ILmax = 20mA
      ");
13 RS=(Vs-Vout)/(Izk+ILmax);//in ohm
14 disp("when the load current will decrease and become
      10 mA, the zener current will increase and
      become 6+10 i.e. 16 mA. Thus the current through

```

series resistance R_s will remain unchanged at 6+20 i.e. 26 mA. Thus voltage drop in series resistance R_s will remain constant. Consequently, the output voltage will also remain constant. ”)
;

Scilab code Exa 4.16 Determine VL IZ and PZ

```
1 //Exa4.16
2 clc;
3 clear;
4 close;
5 //given data
6 Vs=16;//in volts
7 RL=1.2;//in Kohm
8 Rs=1;//in Kohm
9 //If zener open circuited
10 VL=Vs*RL/(Rs+RL);//in Volts
11 disp(VL,"When zener open circuited Voltage across
    load in volts : ");
12 disp("Since voltage across load VL is less than
    breakdown voltage of zener diode i.e. VL < Vz.
    The zener diode will not conduct and VL = 8.73
    Volt");
13 Iz=0;//in mA
14 disp(Iz,"Zener current in mA : ");
15 Pz=VL*Iz;//in watts
16 disp(Pz,"Power in watts : ");
```

Scilab code Exa 4.17 Comment on operation of circuit

```
1 //Exa4.17
2 clc;
```

```

3 clear;
4 close;
5 //given data
6 Vin=20;//in volts
7 Rs=220;//in Kohm
8 Vz=10;//in volts
9 // part (i) RL=50;//in Kohm
10 disp(" For RL=50ohm :");
11 RL=50;//in Kohm
12 VL=Vin*RL/(RL+Rs)
13 disp(" Since voltage across load , VL is less than
        breakdown voltage of zener diode. Zener will not
        conduct.")
14 IR=Vin/(Rs+RL);//in mA
15 IL=IR;//in mA
16 IZ=0;//in mA
17 disp(VL,"VL in volt : ");
18 disp(IL*1000,"IL in mA :");
19 disp(IZ,"Iz in mA: ");
20 disp(IR*1000,"IR in mA :");
21
22 // part (ii) RL=200;//in Kohm
23 disp(" For RL=200ohm : ")
24 RL=200;//in Kohm
25 VL=Vin*RL/(RL+Rs)
26 disp(" voltage across load , if zener diode is open
        circuited.")
27 IR=Vin/(Rs+RL);//in mA
28 IL=IR;//in mA
29 IZ=0;//in mA
30 disp(VL,"VL in volt : ");
31 disp(IL*1000,"IL in mA :");
32 disp(IZ,"Iz in mA: ");
33 disp(IR*1000,"IR in mA :");

```

Scilab code Exa 4.18 Find voltage drop across the resistance

```
1 //Exa4.18
2 clc;
3 clear;
4 close;
5 //given data
6 RL=10;//in Kohm
7 Rs=5;//in Kohm
8 Vin=100;//in Volts
9 disp("Removing the zener diode from the circuit , We
      have :  $V = V_{in} * R_L / (R_L + R_s)$ ");
10 V=Vin*RL/(RL+Rs);//in Volt
11 disp(V,"Voltage V in volts = ");
12 disp("V > Vz So zener diode is in ON stste.");
13 VZ=50;//in Volts
14 VL=VZ;//in volts
15 //Apply KVL
16 VR=100-50;//in Volts
17 VR=50;//in Volts
18 disp(VR,"Hence the voltage dropp across the 5 Kohm
      resistor in Volts is : ");
```

Scilab code Exa 4.19 Find Ri so that VL remain 12V

```
1 //Exa4.19
2 clc;
3 clear;
4 close;
5 //given data
6 RL=120;//in ohm
7 Izmin=20;//in mA
8 Izmax=200;//in mA
9 VL=12;//in Volts
10 VDCmin=15;//in Volts
```

```

11 VDCmax=19.5;//in Volts
12 Vz=12;//in Volts
13 IL=VL/RL;//in Ampere
14 IL=IL*1000;//in mAmpere
15 //For VDCmin = 15 volts
16 VSmin=VDCmin-Vz;//in Volts
17 //For VDCmax = 19.5 volts
18 VSmax=VDCmax-Vz;//in Volts
19 ISmin=Izmin+IL;//in mA
20 Ri=VSmin/ISmin;//in Kohm
21 Ri=Ri*10^3;//in ohm
22 disp(Ri,"The resistance Ri in ohm : ");

```

Scilab code Exa 4.20 Determine range of RL and IL

```

1 //Exa4.20
2 clc;
3 clear;
4 close;
5 //given data
6 VRL=10;//in Volts
7 Vi=50;//in Volts
8 R=1;//in Kohm
9 Vz=10;//in Volts
10 VL=Vz;//in Volts
11 Izm=32;//in mA
12 IR=(Vi-VL)/R;//in mA
13 disp("Load current IL will be maximum when Iz = 0 ")
14 ;
15 Izmin=0;//in mA
16 ILmax=IR-Izmin;//in mA
17 disp(ILmax,"Maximum load current in mA : ");
18 RLmin=VL/ILmax;//in Ohm
19 disp("Load current IL will be minimum when Iz =
    maximum i.e. 32 mA ");

```

```
19 Izmax=32; //in mA
20 ILmin=IR-Izmax; //in mA
21 disp(ILmin,"Minimum load current in mA : ");
22 VL=Vz; //in Volts
23 RLmax=VL/ILmin; //in Ohm
24 disp("Hence range of RL and IL are as follows :");
25 disp("Range of RL in Kohm : From "+string(RLmin)+"
    to "+string(RLmax));
26 disp("Range of IL in mA : From "+string(ILmin)+" to
    "+string(ILmax));
```

Chapter 5

Junction Properties Continued

Scilab code Exa 5.1 Estimate junction width

```
1 //Exa 5.1
2 clc;
3 clear;
4 close;
5 //given data
6 ND=10^17; //in atoms/cm^3
7 NA=0.5*10^16; //in atoms/cm^3
8 Vo=0.7; //in Volts
9 V=-10; //in Volts
10 ND=ND*10^6; //in atoms/m^3
11 NA=NA*10^6; //in atoms/m^3
12 epsilon=8.85*10^-11; //in F/m
13 e=1.6*10^-19; //coulamb
14 //part (i)
15 disp("When no external voltage is applied i.e. V=0")
    ;
16 disp("VB = 0.7 volts");
17 VB=0.7; //in Volts
18 W=sqrt(2*epsilon*VB*(1/NA+1/ND)/e); //in m
19 disp(W,"When no external voltage is applied ,
    Junction width in meter : ");
```

```

20 //part (ii)
21 disp("When external voltage of -10 volt is applied")
    ;
22 disp("VB = Vo-V volts");
23 VB=Vo-V;//in Volts
24 W=sqrt(2*epsilon*VB*(1/NA+1/ND)/e);//in m
25 disp(W,"When external voltage of -10 Volt is applied
    , Junction width in meter : ");

```

Scilab code Exa 5.3 Find new position of fermi level

```

1 //Exa 5.3
2 clc;
3 clear;
4 close;
5 //given data
6 Ecf=0.3;//in Volts
7 T=27+273;//in Kelvin
8 delT=55;//in degree centigrade
9 //formula : Ecf=Ec-Ef=K*T*log(nc/ND)
10 //let K*log(nc/ND)=y
11 //Ecf=Ec-Ef=T*y
12 y=Ecf/T;//assumed
13 Tnew=273+55;//in Kelvin
14 EcfNEW=y*Tnew;//in Volts
15 disp(EcfNEW,"New position of fermi level is(eV) : ")
    ;

```

Scilab code Exa 5.4 Calculate height of potential barrier

```

1 //Exa 5.4
2 clc;
3 clear;

```

```

4 close;
5 //given data
6 ND=8*10^14; //in cm^-3
7 NA=8*10^14; //in cm^-3
8 ni=2*10^13; //in cm^-3
9 T=300; //in Kelvin
10 k=8.61*10^-5; //in eV/K
11 e=1.6*10^-19; //coulomb
12 Vo=k*T*log(ND*NA/ni^2); //in Volts
13 disp(Vo,"Potential barrier in volts : ");

```

Scilab code Exa 5.5 Find electron and hole concentration

```

1 //Exa 5.5
2 clc;
3 clear;
4 close;
5 //given data
6 ND=2*10^16; //in cm^-3
7 NA=5*10^15; //in cm^-3
8 Ao=4.83*10^21; //constant
9 T=300; //in Kelvin
10 EG=1.1; //in eV
11 kT=0.026; //in eV
12 ni=Ao*T^(3/2)*exp(-EG/(2*kT)); //in m^-3
13 ni=ni*10^-6; //in cm^-3
14 p=(ni^2)/ND; //in cm^-3
15 n=(ni^2)/NA; //in cm^-3
16 disp(p,"Hole concentration in cm^-3 : ");
17 disp(n,"electron concentration in cm^-3 : ");
18 disp("Since electron concentration is mote than hole
      concentration , the given Si is of N-type.");
19 //Note : Ans in the book is wrong. Mistake in value
      putting.

```

Scilab code Exa 5.6 Determine junction capacitance

```
1 //Exa 5.6
2 clc;
3 clear;
4 close;
5 //given data
6 CTzero=50; //in pF
7 VR=8; //in Volt
8 VK=0.7; //in Volt
9 n=1/3; //for Si
10 CT=CTzero/((1+VR/VK)^n); //in pF
11 disp(CT," Junction capacitance in pF : ");
```

Chapter 6

Bipolar Junction Transistors

Scilab code Exa 6.1 Determine emitter current

```
1 //Exa 6.1
2 clc;
3 clear;
4 close;
5 //given data
6 IC=20;//in mA
7 Beta=50;//Unitless
8 IB=IC/Beta;//in mA
9 IE=IC+IB;//in mA
10 disp(IE,"Emitter current in mA : ");
```

Scilab code Exa 6.2 Determine emitter current amplification factor and gain factor

```
1 //Exa 6.2
2 clc;
3 clear;
4 close;
5 //given data
```

```

6 IC=0.98; //in mA
7 IB=20; //in uA
8 IB=IB*10^-3; //in mA
9 //part (i)
10 IE=IB+IC; //in mA
11 disp(IE,"Emitter current in mA :");
12 //part (ii)
13 alfa=IC/IE; // unitless
14 disp(alfa,"Current amplification factor : ");
15 //part (iii)
16 Beta=IC/IB; // unitless
17 disp(Beta,"Current gain factor : ");

```

Scilab code Exa 6.3 Determine emitter current and collector current

```

1 //Exa 6.3
2 clc;
3 clear;
4 close;
5 //given data
6 alfaDC=0.98; // unitless
7 ICBO=4; //in uA
8 ICBO=ICBO*10^-3; //in mA
9 IB=50; //in uA
10 IB=IB*10^-3; //in mA
11 //Formula : IC=alfaDC*(IB+IC)+ICBO
12 IC=alfaDC*IB/(1-alfaDC)+ICBO/(1-alfaDC); //in mA
13 IE=IC+IB; //in mA
14 disp(IE,"Emitter current in mA : ");
15 disp(IC,"Collector current in mA : ");

```

Scilab code Exa 6.4 Determine collector current

```

1 //Exa 6.4
2 clc;
3 clear;
4 close;
5 //given data
6 IB=10; //in uA
7 IB=IB*10^-3; //in mA
8 Beta=99; // Unitless
9 ICO=1; //in uA
10 ICO=ICO*10^-3; //in mA
11 //Formula : IC=alfa*(IB+IC)+ICO
12 IC=Beta*IB+(1+Beta)*ICO; //in mA
13 disp(IC," Collector current in mA : ");

```

Scilab code Exa 6.5 Calculate dynamic input resistance

```

1 //Exa 6.5
2 clc;
3 clear;
4 close;
5 //given data
6 delVEB=200; //in Volts
7 delIE=5; //in mA
8 rin=delVEB/delIE; //in ohm
9 disp(rin," Dynamic input resistance in ohm : ");

```

Scilab code Exa 6.6 Determine base and collector current

```

1 //Exa 6.6
2 clc;
3 clear;
4 close;
5 //given data

```

```

6  alfao=0.98; // unitless
7  IC0=10; //in uA
8  IC0=IC0*10^-3; //in mA
9  IE=2; //in mA
10 IC=alfa*IE+IC0; //in mA
11 IB=IE-IC; //in mA
12 disp(IC," Collector current in mA : ");
13 disp(IB*1000," Base current in uA : ");

```

Scilab code Exa 6.7 Determine current gain and base current

```

1  //Exa 6.7
2  clc;
3  clear;
4  close;
5  //given data
6  ICB0=12.5; //in uA
7  ICB0=ICB0*10^-3; //in mA
8  IE=2; //in mA
9  IC=1.97; //in mA
10 alfa=(IC-ICB0)/IE; // unitless
11 IB=IE-IC; //in mA
12 disp(alfa," Current gain : ");
13 disp(IB," Base current in mA : ");

```

Scilab code Exa 6.8 Determine base current

```

1  //Exa 6.8
2  clc;
3  clear;
4  close;
5  //given data
6  RL=4; //in Kohm

```



```
7 VL=3; //in volt
8 alfa=0.96; //unitless
9 IC=VL/RL; //in mA
10 IE=IC/alfa; //in mA
11 IB=IE-IC; //in mA
12 disp(IB,"Base current in mA : ");
```

Scilab code Exa 6.9 Determine base current

```
1 //Exa 6.9
2 clc;
3 clear;
4 close;
5 //given data
6 RL=1; //in Kohm
7 VL=1.2; //in volt
8 Beta=60; //unitless
9 IC=VL/RL; //in mA
10 IB=IC/Beta; //in mA
11 disp(IB*1000,"Base current in uA : ");
```

Scilab code Exa 6.10 Determine collector emitter voltage and base current

```
1 //Exa 6.10
2 clc;
3 clear;
4 close;
5 //given data
6 VCC=10; //in volt
7 RL=800; //in ohm
8 VL=0.8; //in volt
9 alfa=0.96; //unitless
10 //VR=IC*RL
```

```

11 VCE=VCC-VL;//in Volt
12 disp(VCE," Collector-emitter Voltage in volts : ");
13 IC=VL*1000/RL;//in mA
14 Beta=alfa/(1-alfa);//unitless
15 IB=IC/Beta;//in mA
16 disp(IB*1000," Base current in uA : ");

```

Scilab code Exa 6.11 Determine collector current

```

1 //Exa 6.11
2 clc;
3 clear;
4 close;
5 //given data
6 alfao=0.98;//unitless
7 ICO=10;//in uA
8 ICO=ICO*10^-3;//in mA
9 IB=0.22;//in mA
10 IC=(alfao*IB+ICO)/(1-alfao);//in mA
11 disp(IC," Collector current in mA : ");

```

Scilab code Exa 6.12 Calculate dynamic input resistance

```

1 //Exa 6.12
2 clc;
3 clear;
4 close;
5 //given data
6 delVEB=250;//in mVolts
7 delIE=1;//in mA
8 rin=delVEB/delIE;//in ohm
9 disp(rin," Dynamic input resistance in ohm : ");

```

Scilab code Exa 6.13 Calculate dynamic output resistance

```
1 //Exa 6.13
2 clc;
3 clear;
4 close;
5 //given data
6 delVCE=10-5;//in Volts
7 delIC=5.8-5;//in mA
8 rin=delVCE/delIC;//in Kohm
9 disp(rin,"Dynamic output resistance in Kohm : ");
```

Scilab code Exa 6.14 Determine operating point

```
1 //Exa 6.14
2 clc;
3 clear;
4 close;
5 //given data
6 VCC=10;//in volt
7 RC=8;//in Kohm
8 Beta=40;//unitless
9 IB=15;//in uA
10 IB=IB*10^-3;//in mA
11 // For VCE = 0 Volts
12 IC=VCC/RC;//in mA
13 disp(IC,"VCE=0V and IC in mA = ");
14 disp("This gives a point on load line.");
15 //For IC=0 VCE=VCC=10V :
16 disp("For IC=0, VCE=VCC=10V :")
17 disp("This gives another point on load line.");
18 IC=Beta*IB;//in mA
```

```

19 VCE=VCC-IC*RC; //in Volts
20 disp(" Operating point Q is (" +string(VCE)+"V," +
      string(IC)+"mA)");

```

Scilab code Exa 6.15 Find VCE at cut off point

```

1 //Exa 6.15
2 clc;
3 clear;
4 close;
5 //given data :
6 VCC=20; //in Volt
7 RC=3.3*10^3; //in ohm
8 disp(" Applying Kirchoffs Voltage Law : ");
9 disp(" VCC=IC*RC+VCE");
10 disp(" For cut-off point , IC=0");
11 disp(" Therefore , VCC=VCE");
12 VCE=VCC; //in volt
13 disp(VCE," VCE at cut-off point : ");
14 disp(" For Saturation point , VCE = 0");
15 VCE=0; //in volts
16 IC=VCC/RC; //in A
17 disp(IC," IC at saturation point in mA ; ");
18 disp(" Therefore Load line coordinates are given as :
      ");
19 disp(" (" +string(20)+"V," +string(0)+"mA)");
20 disp(" (" +string(VCE)+"V," +string(IC*1000)+"mA)");

```

Scilab code Exa 6.16 Determine VC and VB

```

1 //Exa 6.16
2 clc;
3 clear;

```

```

4 close;
5 //given data :
6 Beta=45; //Unitless
7 VBE=0.7; //in Volt
8 VCC=0; //in Volt
9 RB=10^5; //in ohm
10 RC=1.2*10^3; //in ohm
11 VEE=-9; //in Volt
12 disp("Applying Kirchoffs Voltage Law in input loop
    we have : ");
13 disp("IB*RB+VBE+VEE=0");
14 IB=-(VBE+VEE)/RB; //in mA
15 IC=Beta*IB; //in mA
16 VC=VCC-IC*RC; //in Volts
17 VB=VBE+VEE; //in Volts
18 disp(VC,"VC in volts : ");
19 disp(VB,"VB in volts : ");

```

Scilab code Exa 6.17 Find IB and IC

```

1 //Exa 6.17
2 clc;
3 clear;
4 close;
5 //given data :
6 Beta=100; //Unitless
7 hfe=Beta; //Unitless
8 VBB=5; //in Volt
9 VBE=0.8; //in Volt
10 RB=50*10^3; //in ohm
11 RE=2*10^3; //in ohm
12 VCE=0.2; //in Volt
13 disp("Applying Kirchoffs Voltage Law in input loop
    we have : ");
14 disp("VBB=IB*RB+VBE+IE*RE=IB*RB+VBE+(1+Beta)*IB*RE")

```

```

;
15 disp("IB=(VBB-VBE)/(RB+(1+Beta)*RE)");
16 IB=(VBB-VBE)/(RB+(1+Beta)*RE); //in A
17 disp(IB*1000,"IB in mA : ");
18 disp("Applying Kirchoffs Voltage Law in output loop
we have : ");
19 disp("10-IC(3*10^3)-VCE-IE(2*10^3)=0");
20 IC=(10-0.2)/(5*10^3); //in A
21 disp(IC*1000,"IC in mA : ");
22 disp(Beta*IB,"Beta*Ib in mA = ");
23 disp(IC,"IC = ");
24 disp("IC > Beta*IB. Hence the transistor is in
saturation with the values of IB = 0.0166 mA and
IC = 1.96 mA.")

```

Chapter 7

Field Effect Transistors

Scilab code Exa 7.1 Determine resistance between gate and source

```
1 //Exa 7.1
2 clc;
3 clear;
4 close;
5 //given data :
6 VGS=10; //in Volt
7 IG=0.001; //in uA
8 IG=IG*10^-6; //in A
9 RGS=VGS/IG; //in ohm
10 disp(RGS/10^6, "Resistance between gate and source in
    Mohm ; ");
```

Scilab code Exa 7.2 Calculate AC drain resistance

```
1 //Exa 7.2
2 clc;
3 clear;
4 close;
```

```

5 //given data :
6 delVDS=1.5; //in Volt
7 delID=120; //in uA
8 delID=120*10^-6; //in A
9 rd=delVDS/delID; //in Ohm
10 disp(rd*10^-3,"AC drain resistance of JFET in Kohm :
    ");

```

Scilab code Exa 7.3 Determine Transconductance

```

1 //Exa 7.3
2 clc;
3 clear;
4 close;
5 //given data :
6 VP=-4.5; //in Volt
7 IDSS=10; //in mA
8 IDS=2.5; //in mA
9 disp("From shockleys equation , drain source current ,
    IDS=IDSS*(1-VGS/VP)^2 ");
10 VGS=VP*(1-sqrt(IDS/IDSS)); //in Volt
11 gm=(-2*IDSS/VP)*(1-VGS/VP); //in mA/Volt
12 disp(gm,"Transconductance in mA/Volt : ");

```

Scilab code Exa 7.4 Calculate VGS

```

1 //Exa 7.4
2 clc;
3 clear;
4 close;
5 //given data :
6 gm=10; //in mS
7 IDSS=10; //in uA

```



```

8 IDSS=IDSS-10^-6; //in Ampere
9 disp("VGS(OFF) : VGS=VP");
10 disp("gm=gmo=-2*IDSS/VP=-2*IDSS/VGS(OFF)");
11 VGS_OFF=-2*IDSS/gm
12 disp(round(VGS_OFF),"VGS(OFF) in mV :");

```

Scilab code Exa 7.5 Determine minimum value of VDS

```

1 //Exa 7.5
2 clc;
3 clear;
4 close;
5 //given data :
6 VP=-4; //in Volt
7 IDSS=10; //in mA
8 IDSS=IDSS*10^-3; //in Ampere
9 VGS=-2; //in Volt
10 ID=IDSS*(1-VGS/VP)^2; //in mA
11 disp(ID*1000,"Drain current in mA : ");
12 disp("The minimum value of VDS for pinch-OFF region
      is equal to VP. Thus the minimum value of VDS : "
      );
13 disp(VP,"VDS(min) in volt : ");

```

Scilab code Exa 7.6 Findd values of ID gmo and gm

```

1 //Exa 7.6
2 clc;
3 clear;
4 close;
5 //given data :
6 VP=-3; //in Volt
7 IDSS=8.7; //in mA

```

```

8 IDSS=IDSS*10^-3; //in mA
9 VGS=-1; //in Volt
10 ID=IDSS*(1-VGS/VP)^2; //in Ampere
11 disp(ID*1000,"ID in mA : ")
12 gmo=-2*IDSS/VP; //in mS
13 disp(gmo*1000,"gmo in mS : ");
14 gm=gmo*(1-VGS/VP); //in mS
15 disp(gm*1000,"gm in mS : ");

```

Scilab code Exa 7.7 Findd values of ID and gm

```

1 //Exa 7.7
2 clc;
3 clear;
4 close;
5 //given data :
6 VP=-3; //in Volt
7 IDSS=8.4; //in mA
8 VGS=-1.5; //in Volt
9 ID=IDSS*(1-VGS/VP)^2; //in mA
10 disp(ID,"Drain current in mA : ");
11 gmo=-2*IDSS/VP; //in mS
12 gm=gmo*(1-VGS/VP); //in mS
13 disp(gm,"gm in mS : ");

```

Scilab code Exa 7.8 Find value of VGS and gm

```

1 //Exa 7.8
2 clc;
3 clear;
4 close;
5 //given data :
6 VP=-4.5; //in Volt

```

```

7 IDSS=9; //in mA
8 IDSS=IDSS*10^-3; //in Ampere
9 IDS=3; //in mA
10 IDS=IDS*10^-3; //in Ampere
11 VGS=VP*(1-sqrt(IDS/IDSS)); //in Volt
12 disp(VGS,"IDS = 3 mA when VGS(in Volt) is : ");
13 gm=(-2*IDSS/VP)*(1-VGS/VP); //in mS
14 disp(gm*1000,"IDS = 3 mA when gm(in mS) is : ");

```

Scilab code Exa 7.9 Sketch the transfer Characteristics

```

1 //Exa 7.9
2 clc;
3 clear;
4 close;
5 //given data :
6 VP=-4; //in Volt
7 IDSS=10; //in mA
8 VGS=[0 1 -1 -2 -4];
9 ID=zeros(1,5);
10 for i=1:5
11     ID(i)=IDSS*(1-VGS(i)/VP)^2; //in mA
12 end
13 plot2d(VGS , ID);

```

Scilab code Exa 7.10 Determine Drain current

```

1 //Exa 7.10
2 clc;
3 clear;
4 close;
5 //given data :
6 ID_on=5; //in mA

```

```
7 VGS=6; //in Volt
8 VGS_on=8; //in Volt
9 VGST=4; //in Volt
10 K=ID_on/(VGS_on-VGST)^2; //in mA/V^2
11 ID=K*(VGS-VGST)^2; //in mA
12 disp(ID,"When VGS=6V the drain current in mA : ");
```

Chapter 8

Photonic Devices

Scilab code Exa 8.1 Determine steady state photo current density

```
1 //Exa 8.1
2 clc;
3 clear;
4 close;
5 //given data :
6 NA=10^22; //in atoms/m^3
7 ND=10^22; //in atoms/m^3
8 De=25*10^-4; //in m^2/s
9 Dh=10^-3; //in m^2/s
10 TAUeo=500; //in ns
11 TAUho=100; //in ns
12 ni=1.5*10^16; //in atoms/m^3
13 VR=-10; //in Volt
14 epsilon=11.6*8.854*10^-12; //in F/m
15 e=1.6*10^-19; //in Coulamb
16 VT=26; //in mV
17 GL=10^27; //in m^-3 s^-1
18
19 Le=sqrt(De*TAUeo*10^-9); //in um
20 Le=Le*10^6; //in um
21 Lh=sqrt(Dh*TAUho*10^-9); //in um
```

```

22 Lh=Lh*10^6; //in um
23 Vbi=VT*10^-3*log(NA*ND/ni^2); //in Volt
24 Vo=Vbi; //in Volt
25 VB=Vo-VR; //in Volt
26 W=sqrt((2*epsilon*VB/e)*(1/NA+1/ND)); //in um
27 W=W*10^6; //in um
28 JL=e*(W+Le+Lh)*10^-6*GL; //in A/cm^2
29 disp(JL/10^4,"Steady state photocurrent density in A
    /cm^2 : ");

```

Scilab code Exa 8.2 Determine photo current density

```

1 //Exa 8.2
2 clc;
3 clear;
4 close;
5 //given data :
6 W=25; //in um
7 PhotonFlux=10^21; //in m^2s^-1
8 alfa=10^5; //in m^-1
9 e=1.6*10^-19; //in Coulombs
10 GL1=alfa*PhotonFlux; //in m^-3s^-1
11 GL2=alfa*PhotonFlux*exp(-alfa*W*10^-6); //in m^-3s^-1
12 JL=e*PhotonFlux*(1-exp(-alfa*W*10^-6)); //in mA/cm^2
13 disp(JL/10,"Steady state photocurrent density in mA/
    cm^2 : ");

```

Scilab code Exa 8.3 Determine open circuit voltage

```

1 //Exa 8.3
2 clc;
3 clear;
4 close;

```

```

5 //given data :
6 NA=7.5*10^24; //in atoms/m^3
7 ND=1.5*10^22; //in atoms/m^3
8 De=25*10^-4; //in m^2/s
9 Dh=10^-3; //in m^2/s
10 TAUeo=500; //in ns
11 TAUho=100; //in ns
12 ni=1.5*10^16; //in atoms/m^3
13 VR=-10; //in Volt
14 epsilon=11.6*8.854*10^-12; //in F/m
15 e=1.6*10^-19; //in Coulomb
16 VT=26; //in mV
17 GL=10^27; //in m^-3 s^-1
18
19 Le=sqrt(De*TAUeo*10^-9); //in um
20 Le=Le*10^6; //in um
21 Lh=sqrt(Dh*TAUho*10^-9); //in um
22 Lh=Lh*10^6; //in um
23 JS=e*(ni^2)*(De/(Le*10^-6*NA)+De/(Lh*10^-6*ND)); //in
    A/cm^2
24 JL=12.5; //in mA/cm^2
25 VOC=VT*log(1+JL/JS); //in Volt
26 disp(VOC,"Open circuit voltage in Volt : ");
27 //Note : Answer in the book is wrong.

```

Scilab code Exa 8.4 Determine approximate no of solar cell required

```

1 //Exa 8.4
2 clc;
3 clear;
4 close;
5 //given data :
6
7 disp("Each cell supplies 50 mA at 0.45V. Allowing
    for the voltage drop across the rectifier and

```

```

    series resistor , a maximum output voltage of
    approximately 28V is required. Thus, ");
8 disp("n = Vout/Vcell");
9 Vout=28;//in Volts
10 Vcell=0.45;//in Volt
11 n=Vout/Vcell;//Unitless
12 disp(n,"No. of series connected- cells = ");
13 disp("the charge taken from the batteries over a
    period of 24 hour is 24*0.5 = 12 Ah. thus, the
    charge delivered by the solar cells must be 12
    ampere Hours");
14 disp("Since the solar cells are illuminated only 12
    hours a day, the necessary charging current from
    the solar cell is 12Ah/12h i.e. 1 A");
15 Iout=1;//in A
16 Icell=50;//in mA
17 m=Iout/(Icell*10^-3);//unitless
18 disp(m,"Hence total no. of group of cells in
    parallel , m ");
19 disp(round(m*n),"The total no. of cells required : "
    );
20 //Note : Answer in the book is wrong.

```
